

V7E/LX7-RUB6

V7E/LX7 Option Switch Settings: 1(Pulse/ICT104U/RS232 A0/ccNet)

Supported bill RUB 10, 50, 100, 500, 1000, 5000 6 bills.

V7E/LX7 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject RUB 10	ON											
★ Accept RUB 10	OFF											
★ Reject RUB 50		ON										
★ Accept RUB 50		OFF										
★ Reject RUB 100			ON									
★ Accept RUB 100			OFF									
★ Reject RUB 500				ON								
★ Accept RUB 500				OFF								
★ Reject RUB 1000					ON							
★ Accept RUB 1000					OFF							
★ Reject RUB 5000						ON						
★ Accept RUB 5000						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / RUB 10									OFF	OFF		
2 pulses / RUB 10									ON	OFF		
5 pulses / RUB 10									OFF	ON		
20 pulses / RUB 10									ON	ON		
★ Pulse Speed		50ms LO / 50ms HI									OFF	OFF
		60ms LO / 300ms HI									ON	OFF
		30ms LO / 50ms HI									OFF	ON
		150ms LO / 150ms HI									ON	ON

★ Manufacture setting

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

(3) Default setting.

V7E/LX7-RUB6(Pulse/ICT104U/RS232 A0/ccNet)

DIP SWITCHES SETTING: 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ccNet Mode		ON	ON	
RS232 A0 Mode		OFF	ON	
★ Reserved				ON
				OFF

DIP SWITCHES SETTING: 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
ccNet Mode		ON	ON	
RS232 A0 Mode		OFF	ON	
★ Reserved				ON
				OFF

DIP SWITCHES SETTING: 2(ccNet)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
9600 Baud rate	OFF			
Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
★ ccNet Mode		ON	ON	
RS232 A0 Mode		OFF	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface	ICT104U	Pulse	RS232 A0	ccNet
Bill value				
BV1	RUB 10	RUB 10	RUB 10	RUB 10
BV2	RUB 50	RUB 50	RUB 50	RUB 50
BV3	RUB 100	RUB 100	RUB 100	RUB 100
BV4	RUB 500	RUB 500	RUB 500	RUB 500
BV5	RUB 1000	RUB 1000	RUB 1000	RUB 1000
BV6	RUB 5000	RUB 5000	RUB 5000	RUB 5000

DIP SWITCHES SETTING: 2(RS232 A0)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ccNet Mode		ON	ON	
★ RS232 A0 Mode		OFF	ON	
★ Reserved				ON
				OFF

RS232 A0 INFORMATION

Code	Denomination
1	Reserved
2	Reserved
3	RUB 10
4	RUB 50
5	RUB 100
6	RUB 500
7	RUB 1000
8	RUB 5000

★ Manufacture setting