

SCA1-CAD3

SCA1 DIP SWITCHES SETTING : 1(Pulse/Parallel/RS232)

Supported coin CAD 0.25, 1, 2 3 coins.

DIP SW	Pulse Ratio				Pulse Ratio (Bonus)			
	1	2	3	4	5	6	7	8
CH1	1	1/4	1	1	1/2	1/2	1/2	1/4
CH2	1	1/2	1	1	1	1	1	1/2
CH3	4	1/2	2	2	1	3	2	1+1/2
CH4	4	1	4	2	2	5+1	4+1	2+1
CH5	8	2	8	4	4+1	10+2	5+1	4+2
CH6	8	2	8	4	N/A	N/A	8+2	5+2
CH7	8	4	10	10	N/A	N/A	10+2	N/A
CH8	10	5	10	10	N/A	N/A	N/A	N/A

Note: To setup CAD 0.25, 1, 2 is recommended.

MODE		DIP SW	SW4	SW5	SW6
Operation Mode	Pulse Speed 50ms		OFF	OFF	
	Pulse Speed 100ms		ON	OFF	
Study Mode			ON	ON	
Pulse Normal Low					OFF
Pulse Normal High					ON

Note: Please refer to the installation guide for Study Mode operation explanation.