
















GEL6 (ccTalk/Parallel)

SCA1 DIP SWITCHES SETTING : 1

Supported coin  0.05, 0.1, 0.2, 0.5, 1, 2 6 coins.

| | FUNCTION | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW9 | SW10 |
|---|--|-----|-----|-----|-----|-----|-----|-----|-----|-----|------|
| ★ | Accept  5 tetris | OFF | | | | | | | | | |
| | Reject  5 tetris | ON | | | | | | | | | |
| ★ | Accept  10 tetris | | OFF | | | | | | | | |
| | Reject  10 tetris | | ON | | | | | | | | |
| ★ | Accept  20 tetris | | | OFF | | | | | | | |
| | Reject  20 tetris | | | ON | | | | | | | |
| ★ | Accept  50 tetris (O) | | | | OFF | | | | | | |
| | Reject  50 tetris (O) | | | | ON | | | | | | |
| ★ | Accept  50 tetris (N) | | | | | OFF | | | | | |
| | Reject  50 tetris (N) | | | | | ON | | | | | |
| ★ | Accept  1 lari | | | | | | OFF | | | | |
| | Reject  1 lari | | | | | | ON | | | | |
| ★ | Accept  2 lari | | | | | | | OFF | | | |
| | Reject  2 lari | | | | | | | ON | | | |
| ★ | Reserved | | | | | | | | OFF | | |
| | Reserved | | | | | | | | ON | | |
| | ccTalk Protocol | | | | | | | | | OFF | |
| | Paralle Protocol | | | | | | | | | ON | |
| ★ | Block 0 | | | | | | | | | | OFF |
| | Block 1 | | | | | | | | | | ON |

★ Manufacture setting

Currency Assign Data

| Channel Currency | Paralle |
|---------------------------|---------|
| Channel 1 : 5 tetris | 1 |
| Channel 2 : 10 tetris | 1 |
| Channel 3 : 20 tetris | 1 |
| Channel 4 : 50 tetris (O) | 2 |
| Channel 5 : 50 tetris (N) | 2 |
| Channel 6 : 1 lari | 3 |
| Channel 7 : 2 lari | 4 |

DIP SWITCHES SETTING : 2

| | FUNCTION | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW9 | SW10 |
|---|-------------|-----|-----|-----|-----|-----|-----|-----|-----|-----|------|
| ★ | Reserved | OFF | | | | | | | | | |
| | Reserved | ON | | | | | | | | | |
| ★ | Reserved | | OFF | | | | | | | | |
| | Reserved | | ON | | | | | | | | |
| ★ | Reserved | | | OFF | | | | | | | |
| | Reserved | | | ON | | | | | | | |
| ★ | Reserved | | | | OFF | | | | | | |
| | Reserved | | | | ON | | | | | | |
| ★ | Reserved | | | | | OFF | | | | | |
| | Reserved | | | | | ON | | | | | |
| ★ | Reserved | | | | | | OFF | | | | |
| | Reserved | | | | | | ON | | | | |
| ★ | Reserved | | | | | | | OFF | | | |
| | Reserved | | | | | | | ON | | | |
| ★ | User define | | | | | | | | | ON | ON |
| ★ | ICT | | | | | | | | | OFF | OFF |
| | Mode 1 | | | | | | | | | ON | OFF |
| | Mode 2 | | | | | | | | | OFF | ON |

★ Manufacture setting.
SW9 - SW10 : ccTalk for Sorter Setup. (Top Entry.)