

TAO-A.V-AED5

TAO-A.V Option Switch Settings: 1(Pulse/MDB/ccNet)

Supported bill AED 5, 10, 20, 50, 100 5bills.

TAO-V dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject AED 5	ON											
★ Accept AED 5	OFF											
★ Reject AED 10		ON										
★ Accept AED 10		OFF										
★ Reject AED 20			ON									
★ Accept AED 20			OFF									
★ Reject AED 50				ON								
★ Accept AED 50				OFF								
★ Reject AED 100					ON							
★ Accept AED 100					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Pulse Moded	Other Moded											
★ Harness Disable	BA stops working when fishing						ON					
★ Harness Enable	Normal						OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / AED 5									OFF	OFF		
★ 2 pulses / AED 5									ON	OFF		
★ 5 pulses / AED 5									OFF	ON		
★ 10 pulses / AED 5									ON	ON		
★ Interface Timing Conversion	50ms LO / 50ms HI										OFF	OFF
	60ms LO / 300ms HI										ON	OFF
	30ms LO / 50ms HI										OFF	ON
	150ms LO / 150ms HI										ON	ON

★ Manufacture setting

After setting dip switch of the credit pulses,you should reset the bill acceptor again.

◆ Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

BV1=AED 5, BV2=AED 10, BV3=AED 20, BV4=AED 50, BV5=AED 100

TAO-A.V-AED5(Pulse/MDB/ccNet)

Interface Settings: 2(Pulse) Currency Assign Data

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ccNet Mode		OFF	ON	
MDB Interface		ON	ON	
Reserved		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Bill value	ccNet	Pulse	MDB
BV1	AED 5	AED 5	AED 5
BV2	AED 10	AED 10	AED 10
BV3	AED 20	AED 20	AED 20
BV4	AED 50	AED 50	AED 50
BV5	AED 100	AED 100	AED 100

Interface Settings: 2(ccNet)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ccNet Mode		OFF	ON	
MDB Interface		ON	ON	
Reserved		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

TAO-V-AED5

Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
ccNet Mode		OFF	ON	
★ MDB Interface		ON	ON	
Reserved		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting