

TAO-A.V-IDR7

TAO-A.V Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill Rp 1000, 2000, 5000, 10000, 20000, 50000, 100000 7bills.

TAO-V dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject Rp 1000 & 2000 & 5000 & 10000	ON											
★	Accept Rp 1000 & 2000 & 5000 & 10000	OFF											
★	Reject Rp 20000		ON										
★	Accept Rp 20000		OFF										
★	Reject Rp 50000			ON									
★	Accept Rp 50000			OFF									
★	Reject Rp 100000				ON								
★	Accept Rp 100000				OFF								
★	High Acceptance (Note.3)				ON								
★	High Security				OFF								
★	Reserved				ON								
★	Reserved				OFF								
	Pulse Mode	Other Mode											
★	Harness Disable	BA stops working when fishing								ON			
★	Harness Enable	Normal								OFF			
★	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulses / Rp 1K								OFF	OFF			
★	5 pulses / Rp 1K								ON	OFF			
★	10 pulses / Rp 1K								OFF	ON			
★	20 pulses / Rp 1K								ON	ON			
★	Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
		60ms LO / 300ms HI								ON	OFF		
		30ms LO / 50ms HI								OFF	ON		
		150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

Note : (1) Default setting

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

(4) The function(credit divide by1000) is only used at standard MDB mode

(5) i. Special MDB setting mode works for vending machine. It can't accept IDR 100,000 bill in this mode.
ii.The function(Normal credit/Credit divide) is disable when BA works at special MDB Setting Mode.

Appendix

TAO-A.V-IDR7(Pulse/ICT104V/ICT104U/MDB)

Interface Settings: 2(Pulse) Currency Assign Data

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT104V Interface		OFF	ON	
	ICT104U Interface		OFF	OFF	
	MDB Interface		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Bill value	MDB	Pulse	ICT104V	ICT104U
BV1	1000	1000	1000	1000
BV2	2000	2000	2000	2000
BV3	5000	5000	5000	5000
BV4	10000	10000	10000	10000
BV5	20000	20000	20000	20000
BV6	50000	50000	50000	50000
BV7	100000	100000	100000	100000

Interface Settings: 2(ICT104V)

	INTERFACE	SW1	SW2	SW3	SW4
★	Not Used	ON			
	Not Used	OFF			
	Pulse Mode		ON	OFF	
★	ICT104V Interface		OFF	ON	
	ICT104U Interface		OFF	OFF	
	MDB Interface		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Settings: 2(ICT104U)

	INTERFACE	SW1	SW2	SW3	SW4
★	Not Used	ON			
	Not Used	OFF			
	Pulse Mode		ON	OFF	
	ICT104V Interface		OFF	ON	
★	ICT104U Interface		OFF	OFF	
	MDB Interface		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

TAO-V-IDR7

Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Normal Credit	ON			
	Credit divide by 1000 (MDB only) (Note.4)	OFF			
	Pulse Mode		ON	OFF	
	ICT104V Interface		OFF	ON	
	ICT104U Interface		OFF	OFF	
★	MDB Interface		ON	ON	
	Special MDB Setting(Base 5) (Note.5)				ON
★	Normal MDB Setting				OFF

★ Manufacture setting