

TAO-A.V-MXN4(MXN2+USD2)

TAO-A.V Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill N\$ 20, 50 2bills.
USD 1, 5 2bills.

TAO-V dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject USD 1	ON											
★ Accept USD 1	OFF											
★ Reject N\$ 20		ON										
★ Accept N\$ 20		OFF										
★ Reject N\$ 50			ON									
★ Accept N\$ 50			OFF									
★ Reject USD 5				ON								
★ Accept USD 5				OFF								
★ Reserved				ON								
★ Reserved				OFF								
★ Reserved				ON								
★ Reserved				OFF								
Pulse Mode	Other Mode											
Harness Disable	BA stops working when fishing				ON							
★ Harness Enable	Normal				OFF							
★ Inhibit Active High							ON					
★ Inhibit Active Low							OFF					
★ 1 pulse / N\$ 10 / USD \$1								OFF	OFF			
★ 2 pulses / N\$ 10 / USD \$1								ON	OFF			
★ 5 pulses / N\$ 10 / USD \$1								OFF	ON			
★ 10 pulses / N\$ 10 / USD \$1								ON	ON			
★ Interface Timing Conversion	50ms HI / 50ms LO								OFF		OFF	
	300ms HI / 60ms LO								ON		OFF	
	50ms HI / 30ms LO								OFF		ON	
	150ms HI / 150ms LO								ON		ON	

★ Default setting

Use 2nd dip switch of the internal dip-switch to change different interface protocol.

◆ Note : (1) For Accepting US Dollars, make sure you have dip 5 set to ON position.

(Exchange Rate on USD to MXP is 1:15 for MDB Mode)

TAO-A.V-MXN4(MXN2+USD2)(Pulse/ICT104V/ICT104U/MDB)

Interface Settings: 2(Pulse) Currency Assign Data

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
ICT104V Mode		ON	ON	
MDB Mode		OFF	OFF	
★ Reserved				ON
				OFF

Interface Bill value	ICT104U	Pulse	MDB	ICT104V
BV1	USD \$1	USD \$1	USD \$1	USD \$1
BV2	N\$ 20	N\$ 20	N\$ 20	N\$ 20
BV3	N\$ 50	N\$ 50	N\$ 50	N\$ 50
BV4	USD \$5	USD \$5	USD \$5	USD \$5

★ Manufacture setting

Interface Settings: 2(ICT104U) Interface Settings: 2(ICT104V)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
★ ICT104V Mode		ON	ON	
MDB Mode		OFF	OFF	
★ Reserved				ON
				OFF

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
★ ICT104V Mode		ON	ON	
MDB Mode		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

★ Manufacture setting

Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100	ON			
Decimal Point Position (DPP) = 2				
Scaling Factor (SF) = 100	OFF			
Decimal Point Position (DPP) = 2				
Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
ICT104V Mode		ON	ON	
★ MDB Mode		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting