

TAO-A.V-TTD6

TAO-A.V Option Switch Settings: 1(Pulse/ICT104V/MDB/ICT104U)

Supported bill TT\$ 1, 5, 10, 20, 50, 100 6bills.

TAO-A.V dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject TT\$ 1	ON											
★ Accept TT\$ 1	OFF											
★ Reject TT\$ 5		ON										
★ Accept TT\$ 5		OFF										
★ Reject TT\$ 10 & 20			ON									
★ Accept TT\$ 10 & 20			OFF									
★ Reject TT\$ 50				ON								
★ Accept TT\$ 50				OFF								
★ Reject TT\$ 100					ON							
★ Accept TT\$ 100					OFF							
★ Reserved					ON							
★ Reserved					OFF							
★ Pulse Mode	Other Mode											
★ Harness Disable	BA stops working when fishing				ON							
★ Harness Enable	Normal				OFF							
★ Inhibit Active High							ON					
★ Inhibit Active Low							OFF					
★ 1 pulse / TT\$ 1								OFF	OFF			
★ 2 pulses / TT\$ 1								ON	OFF			
★ 4 pulses / TT\$ 1								OFF	ON			
★ 20 pulses / TT\$ 1								ON	ON			
★ Interface Timing Conversion	50ms LO / 50ms HI									OFF	OFF	
	60ms LO / 300ms HI									ON	OFF	
	30ms LO / 50ms HI									OFF	ON	
	150ms LO / 150ms HI									ON	ON	

★ Manufacture setting

◆ Note.1: Default setting

Note.2: Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

TAO-A.V-TTD6(Pulse/ICT104V/MDB/ICT104U)

Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT104V Interface		OFF	ON	
ICT104U Interface		OFF	OFF	
MDB Interface		ON	ON	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

Interface Settings: 2(ICT104V)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104V Interface		OFF	ON	
ICT104U Interface		OFF	OFF	
MDB Interface		ON	ON	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	Pulse	MDB	ICT104V
BV1	TT\$ 1	TT\$ 1	TT\$ 1	TT\$ 1
BV2	TT\$ 5	TT\$ 5	TT\$ 5	TT\$ 5
BV3	TT\$ 10	TT\$ 10	TT\$ 10	TT\$ 10
BV4	TT\$ 20	TT\$ 20	TT\$ 20	TT\$ 20
BV5	TT\$ 100	TT\$ 100	TT\$ 100	TT\$ 100
BV6	TT\$ 50	TT\$ 50	TT\$ 50	TT\$ 50

Interface Settings: 2(ICT104U)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104V Interface		OFF	ON	
ICT104U Interface		OFF	OFF	
MDB Interface		ON	ON	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

TAO-V-TTD6

Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100	ON			
Decimal Point Position (DPP) = 2				
Scaling Factor (SF) = 1	OFF			
Decimal Point Position (DPP) = 0				
Pulse Mode		ON	OFF	
ICT104V Interface		OFF	ON	
ICT104U Interface		OFF	OFF	
★ MDB Interface		ON	ON	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting