

TAO-V-ARS6

TAO-V Option Switch Settings: 1(Pulse/MDB)

Supported bill ARS 2, 5, 10, 20, 50, 100 6bills.

TAO-V dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject ARS 2 & 5	ON											
	Accept ARS 2 & 5	OFF											
★	Reject ARS 10		ON										
★	Accept ARS 10		OFF										
★	Reject ARS 20			ON									
★	Accept ARS 20			OFF									
★	Reject ARS 50				ON								
★	Accept ARS 50				OFF								
★	Reject ARS 100				ON								
★	Accept ARS 100				OFF								
★	Reserved				ON								
★	Reserved				OFF								
★	Harness Disable					ON							
★	Harness Enable					OFF							
★	Inhibit Active High						ON						
★	Inhibit Active Low						OFF						
★	1 pulse / ARS 1							OFF	OFF				
	2 pulse / ARS 1							ON	OFF				
	4 pulse / ARS 1							OFF	ON				
	20 pulse / ARS 1							ON	ON				
★	Interface Timing Conversion	50ms on / 50ms off								OFF		OFF	
		60ms on / 300ms off								ON		OFF	
		30ms on / 50ms off								OFF		ON	
		150ms on / 150ms off								ON		ON	

★ Manufacture setting

◆ Note : (1) Please reset the bill acceptor after any changes on Dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

TAO-V-ARS6(Pulse/MDB)

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	MDB Interface		OFF		
★	Reserved			ON	
				OFF	
★					ON
★					OFF

★ Manufacture setting

Interface Settings: 2(MDB)

	INTERFACE	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON		
★	MDB Interface		OFF		
★	Reserved			ON	
				OFF	
★					ON
★					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB
BV1	ARS 2	ARS 2
BV2	ARS 5	ARS 5
BV3	ARS 10	ARS 10
BV4	ARS 20	ARS 20
BV5	ARS 50	ARS 50
BV6	ARS 100	ARS 100