

TAO-V-PEN3

TAO-V Option Switch Settings: 1(Pulse/MDB)

Supported bill PEN 10, 20, 50 3bills.

TAO-V dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject PEN 10	ON											
	Accept PEN 10	OFF											
★	Reject PEN 20		ON										
★	Accept PEN 20		OFF										
★	Reject PEN 50			ON									
★	Accept PEN 50			OFF									
	Reserved				ON								
★	Reserved				OFF								
	Reserved				ON								
★	Reserved				OFF								
★	Reserved				ON								
★	Reserved				OFF								
	Harness Disable					ON							
★	Harness Enable					OFF							
	Inhibit Active High						ON						
★	Inhibit Active Low						OFF						
★	1 pulse / PEN 10							OFF	OFF				
	2 pulse / PEN 10							ON	OFF				
	5 pulse / PEN 10							OFF	ON				
	20 pulse / PEN 10							ON	ON				
★	Interface Timing Conversion	50ms LO / 50ms HI									OFF	OFF	
		60ms LO / 300ms HI									ON	OFF	
		30ms LO / 50ms HI									OFF	ON	
		150ms LO / 150ms HI									ON	ON	

★ Manufacture setting

◆ Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

TAO-V-PEN3(Pulse/MDB)

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	MDB Interface		OFF		
★	Reserved			ON	
				OFF	
					ON
★					OFF

★ Manufacture setting

Interface Settings: 2(MDB)

	INTERFACE	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON		
★	MDB Interface		OFF		
★	Reserved			ON	
				OFF	
					ON
★					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB
BV1	PEN 10	PEN 10
BV2	PEN 20	PEN 20
BV3	PEN 50	PEN 50