

V7E-COP6

V7E Option Switch Settings: 1(Pulse/ICT/M.D.B)

Supported bill Col\$ 1000, 2000, 5000, 10000, 20000, 50000 6bills.

V7E dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject Col\$ 1000 & 2000	ON											
★ Accept Col\$ 1000 & 2000	OFF											
★ Reject Col\$ 5000		ON										
★ Accept Col\$ 5000		OFF										
★ Reject Col\$ 10000			ON									
★ Accept Col\$ 10000			OFF									
★ Reject Col\$ 20000				ON								
★ Accept Col\$ 20000				OFF								
★ Reject Col\$ 50000					ON							
★ Accept Col\$ 50000					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / Col\$ 1000									OFF	OFF		
★ 2 pulse / Col\$ 1000									ON	OFF		
★ 4 pulse / Col\$ 1000									OFF	ON		
★ 20 pulse / Col\$ 1000									ON	ON		
★ Pulse Speed	50ms on / 50ms off								OFF	OFF		
	60ms on / 300ms off								ON	OFF		
	30ms on / 50ms off								OFF	ON		
	150ms on / 150ms off								ON	ON		

★ Manufacture setting

◆ Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

V7E-COP6

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ ICT Interface		OFF	ON	
Pulse Mode		ON	OFF	
M.D.B Interface		ON	ON	
★ Reserved				ON
				OFF

DIP SWITCHES SETTING : 3(ICT)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
★ ICT Interface		OFF	ON	
Pulse Mode		ON	OFF	
M.D.B Interface		ON	ON	
★ Reserved				ON
				OFF

DIP SWITCHES SETTING : 4(M.D.B)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	OFF			
★ Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0				
★ ICT Interface		OFF	ON	
Pulse Mode		ON	OFF	
M.D.B Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

◆ Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

