

V7E-RON3

V7E Option Switch Settings: 1(Pulse/ICT/M.D.B)

Supported bill Lei 1, 5, 10 3bills.

V7E dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject Lei 1	ON											
	Accept Lei 1	OFF											
	Reject Lei 5		ON										
★	Accept Lei 5		OFF										
	Reject Lei 10			ON									
★	Accept Lei 10			OFF									
	Reserved				ON								
★	Reserved				OFF								
	Reserved					ON							
★	Reserved					OFF							
	Reserved						ON						
★	Reserved						OFF						
	Harness Disable							ON					
★	Harness Enable							OFF					
	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / Lei 1									OFF	OFF		
	5 pulse / Lei 1									ON	OFF		
	10 pulse / Lei 1									OFF	ON		
	20 pulse / Lei 1									ON	ON		
★	Pulse Speed	50ms on / 50ms off								OFF	OFF		
		60ms on / 300ms off								ON	OFF		
		30ms on / 50ms off								OFF	ON		
		150ms on / 150ms off								ON	ON		

★ Manufacture setting

◆ Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

V7E-RON3

DIP SWITCHES SETTING : 2(Pulse) Currency Assign Data

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
	ICT Interface		OFF	ON	
★	Pulse Mode		ON	OFF	
	M.D.B Interface		ON	ON	
★	Reserved			ON	
				OFF	

Interface Bill value	Pulse	MDB	ICT104
BV1	Lei 1	Lei 1	Lei 1
BV2	Lei 5	Lei 5	Lei 5
BV3	Lei 10	Lei 10	Lei 10

DIP SWITCHES SETTING : 2(ICT)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	ICT Interface		OFF	ON	
	Pulse Mode		ON	OFF	
	M.D.B Interface		ON	ON	
★	Reserved			ON	
				OFF	

DIP SWITCHES SETTING : 2(M.D.B)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	ICT Interface		OFF	ON	
	Pulse Mode		ON	OFF	
★	M.D.B Interface		ON	ON	
★	Reserved			ON	
				OFF	

★ Manufacture setting

◆ Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.