

A6E-TTD6

A6E Option Switch Settings: 1 (Pulse/5V ENABLE/ICT002U)

Supported bill TTD 1, 5, 10, 20, 50, 100 6bills.

A6E dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
	Reject TTD 1	ON											
★	Accept TTD 1	OFF											
	Reject TTD 5		ON										
★	Accept TTD 5		OFF										
	Reject TTD 10 & 20			ON									
★	Accept TTD 10 & 20			OFF									
	Reject TTD 50				ON								
★	Accept TTD 50				OFF								
	Reject TTD 100					ON							
★	Accept TTD 100					OFF							
	Interface(VCP) Mode	(Note.3)				ON							
★	Diagnostic Mode	(Note.4)				OFF							
	Harness Disable							ON					
★	Harness Enable							OFF					
	Inhibit Active High	(Note.5)						ON					
★	Inhibit Active Low							OFF					
★	1 pulse / TTD 1							OFF	OFF				
	2 pulse / TTD 1							ON	OFF				
	4 pulse / TTD 1							OFF	ON				
	20 pulse / TTD 1							ON	ON				
★	Pulse Speed	50ms LO / 50ms HI								OFF	OFF		
		60ms LO / 300ms HI								ON	OFF		
		30ms LO / 50ms HI								OFF	ON		
		150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

◆ Default setting(Factory configuration has all switches in the OFF position.)

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

(3) Interface(VCP) Mode is for USB connection of ICT002U.

(4) Diagnostic Mode is for USB connection of Autotest tool.

(5) SW8 of the 8-switch DIP is for pulse 5V Enable only.

A6E-TTD6(Pulse/5V Enable/ICT002U)

Remove the front cover and the dip-switch is on the CPU board.

A6E Interface Settings: 2 (Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	ICT002U Mode		OFF		
	Reserved			ON	
★	Reserved			OFF	
★	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

A6E Interface Settings: 4 (ICT002U)

	INTERFACE	SW1	SW2	SW3	SW4
	Reserved	ON			
★	Reserved	OFF			
	Pulse Mode		ON		
★	ICT002U Mode		OFF		
	Reserved			ON	
★	Reserved			OFF	
★	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT	Pulse
BV1	TTD 1	TTD 1
BV2	TTD 5	TTD 5
BV3	TTD 10	TTD 10
BV4	TTD 20	TTD 20
BV5	TTD 100	TTD 100
BV6	TTD 50	TTD 50