

BR2300-GMD5

BR2300 DIP SWITCHES SETTING : (MDB/ICT-BC/ccTalk)

Supported bill GMD 10, 20, 50, 100, 200 5 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10	
	Reject GMD 10 & 20	ON										
★	Accept GMD 10 & 20	OFF										
	Reject GMD 50		ON									
★	Accept GMD 50		OFF									
	Reject GMD 100			ON								
★	Accept GMD 100			OFF								
	Reject GMD 200				ON							
★	Accept GMD 200				OFF							
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	(MDB only)				ON						
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0					OFF						
★	Normal						OFF	OFF				
	Load Banknote to Recycle						ON	OFF				
	Load Banknote to Stacker						OFF	ON				
	Unload Banknote to Stacker						ON	ON				
★	ccTalk								ON	OFF		
	ccTalk (Note.1)								OFF	ON		
★	MDB Mode								OFF	OFF		
★	ICT-BC Mode								ON	ON		
	ccTalk	MDB Mode				ICT-BC Mode						
★	Encryption MODE	★ Virtual MDB Recycler Function (Note.2)				Connect with MDB Connector				ON		
	Decrypt MODE	Standard MDB Recycler Function				★ Connect with RS232 Connector				OFF		

★ Manufacture setting

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note. 1: Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

Note.2: Recycled Banknote represents virtual MDB coin type.

Note.3: Calibrate card is needed.

BR2300 - GMD5 (MDB/ICT-BC/ccTalk)

Currency Assign Data

Interface Bill value	MDB	ICT-BC	ccTalk	Recycler banknote inventory	
BV1	GMD 10	GMD 10	GMD 10	GMD 10	45 pcs
BV2	GMD 20	GMD 20	GMD 20	GMD 20	45 pcs
BV3	GMD 50	GMD 50	GMD 50	GMD 50	45 pcs
BV4	GMD 100	GMD 100	GMD 100	GMD 100	45 pcs
BV5	GMD 200	GMD 200	GMD 200	GMD 200	45 pcs