

BRV-KWD4

BRV Option Switch Settings: 1(ICT-BC/MDB/JPSTD Dummy)

Supported bill KWD 0.25, 0.5, 1, 5 4bills.

BRV dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject KWD 0.25	ON											
★ Accept KWD 0.25	OFF											
★ Reject KWD 0.5		ON										
★ Accept KWD 0.5		OFF										
★ Reject KWD 1			ON									
★ Accept KWD 1			OFF									
★ Reject KWD 5				ON								
★ Accept KWD 5				OFF								
★ Reserved					ON							
★ Reserved					OFF							
★ Normal						OFF	OFF					
★ Load Banknote to Recycle						ON	OFF					
★ Load Banknote to Stacker						OFF	ON					
★ Unload Banknote to Stacker						ON	ON					
★ Reserved								ON				
★ Reserved								OFF				
MDB Mode	SW1	SW2	SW3	SW4	JPSTD Dummy Mode							
★ Reserved	ON				★ 255 Bank Note Limitation Per Transaction	ON	ON	ON				
★ Reserved	OFF				1 Bank Note Limitation Per Transaction	OFF	OFF	OFF				
★ Reserved		ON			2 Bank Note Limitation Per Transaction	ON	OFF	OFF				
★ Reserved		OFF			3 Bank Note Limitation Per Transaction	OFF	ON	OFF				
★ Reserved			ON		4 Bank Note Limitation Per Transaction	ON	ON	OFF				
★ Reserved				ON	5 Bank Note Limitation Per Transaction	OFF	OFF	ON				
★ Reserved				OFF	6 Bank Note Limitation Per Transaction	ON	OFF	ON				
★ Reserved					7 Bank Note Limitation Per Transaction	OFF	ON	ON				
★ Virtual MDB Recycler Function (Note.4)				ON	No Refund After the Deal							ON
★ Standard MDB Recycler Function				OFF	★ Refund After the Deal							OFF

★ Manufacture setting

Note : (1) After setting dip switch of the credit pulses, you should reset the bill acceptor again.

(2) Please reset the bill acceptor after set the dip switch.

(3) Calibrate card is needed.

(4) Recycled Banknote represents virtual MDB coin type.

(5) Medium Security mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

BRV-KWD4(ICT-BC/MDB/JPSTD Dummy)

Interface Settings: 2(ICT-BC)

INTERFACE	SW5	SW6	SW7	SW8
★ Reserved	ON			
★ Reserved	OFF			
★ Connect with MDB Connector		ON		
★ Connect with RS232 Connector		OFF		
★ MDB Mode			OFF	OFF
★ JPSTD Dummy Mode			OFF	ON
★ Reserved			ON	OFF
★ ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(JPSTD Dummy)

INTERFACE	SW5	SW6	SW7	SW8
★ Escrow (JPSTD Dummy Mode)	ON			
★ No Escrow (JPSTD Dummy Mode)	OFF			
★ Reserved		ON		
★ Reserved		OFF		
★ MDB Mode			OFF	OFF
★ JPSTD Dummy Mode			OFF	ON
★ Reserved			ON	OFF
★ ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB)

INTERFACE	SW5	SW6	SW7	SW8
★ Scaling Factor (SF)= 100 Decimal Point Position (DPP)= 2	ON			
Scaling Factor (SF)= 1000 Decimal Point Position (DPP)= 3	OFF			
★ Reserved		ON		
★ Reserved		OFF		
★ MDB Mode			OFF	OFF
★ JPSTD Dummy Mode			OFF	ON
★ Reserved			ON	OFF
★ ICT-BC Mode			ON	ON

★ Manufacture setting

Currency Assign Data

Interface Bill value	JPSTD Dummy	ICT-BC	MDB	Recycler banknote inventory	
	BV1	KWD 0.25	KWD 0.25	KWD 0.25	KWD 0.25
BV2	KWD 0.5	KWD 0.5	KWD 0.5	KWD 0.5	40 pcs
BV3	KWD 1	KWD 1	KWD 1	KWD 1	35 pcs
BV4	KWD 5	KWD 5	KWD 5	KWD 5	35 pcs