BRV-THB4

BRV Option Switch Settings: 1(ICT-BC/MDB/JPSTD Dummy/MDB Dummy)

Supported bill THB 20, 50, 100, 500 4bills.

BRV dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
	Reject THB 20	ON											
★	Accept THB 20	OFF											
	Reject THB 50		ON										
★	Accept THB 50		OFF										
	Reject THB 100			ON									
★	Accept THB 100			OFF									
	Reject THB 500				ON								
★	Accept THB 500				OFF								
	Reserved					ON							
★	Reserved					OFF							
★	Normal						OFF	OFF					
	Load Banknote to Recycle						ON	OFF					
	Load Banknote to Stacker						OFF	ON					
	Unload Banknote to cash out						ON	ON					
	Reserved								ON				
★	Reserved								OFF				

	MDB Mode	MDB Dummy Mode	SW1	SW2	SW3	SW4		JPSTD Dummy Mode				
	Reserved	Reserved	ON				★	255 Bank Note Limitation Per Transaction	ON	ON	ON	
★	Reserved	Reserved	OFF					1 Bank Note Limitation Per Transaction	OFF	OFF	OFF	
	Reserved	Reserved		ON				2 Bank Note Limitation Per Transaction	ON	OFF	OFF	
★	Reserved	Reserved		OFF				3 Bank Note Limitation Per Transaction	OFF	ON	OFF	
	Reserved	Reserved			ON			4 Bank Note Limitation Per Transaction	ON	ON	OFF	
★	Reserved	Reserved			OFF			5 Bank Note Limitation Per Transaction	OFF	OFF	ON	
	Virtual MDB (Note.4) Recycler Function	No Refund After the Deal				ON		6 Bank Note Limitation Per Transaction	ON	OFF	ON	ON
★	Standard MDB Recycler Function	★ Refund After the Deal				OFF		7 Bank Note Limitation Per Transaction	OFF	ON	ON	OFF
								★ Refund After the Deal				

★ Manufacture setting

Note：(1) After setting dip switch of the credit pulses,you should reset the bill acceptor again.
(2) Please reset the bill acceptor after set the dip switch.
(3) Calibration card is needed.
(4) Recycled Banknote represents virtual MDB coin type.
(5) Virtual Coin Changer： Scaling Factor = 1, Decimal Point Position = 0.

BRV-THB4(ICT-BC/MDB/JPSTD Dummy/MDB Dummy)

Interface Settings: 2(ICT-BC)

	INTERFACE	SW5	SW6	SW7	SW8
	Reserved	ON			
★	Reserved	OFF			
	Connect with MDB Connector		ON		
★	Connect with RS232 Connector		OFF		
	MDB Mode			OFF	OFF
	JPSTD Dummy Mode			OFF	ON
	MDB Dummy Mode			ON	OFF
★	ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(JPSTD Dummy)

	INTERFACE	SW5	SW6	SW7	SW8
	Escrow (JPSTD Dummy Mode)	ON			
★	No Escrow (JPSTD Dummy Mode)	OFF			
	Reserved		ON		
★	Reserved		OFF		
	MDB Mode			OFF	OFF
★	JPSTD Dummy Mode			OFF	ON
	MDB Dummy Mode			ON	OFF
	ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB)

	INTERFACE	SW5	SW6	SW7	SW8
★	Scaling Factor (SF)= 100 Decimal Point Position (DPP)= 2	ON			
	Scaling Factor (SF)= 1 Decimal Point Position (DPP)= 0	OFF			
	Reserved		ON		
★	Reserved		OFF		
★	MDB Mode			OFF	OFF
	JPSTD Dummy Mode			OFF	ON
	MDB Dummy Mode			ON	OFF
	ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB Dummy)

	INTERFACE	SW5	SW6	SW7	SW8
	Reserved	ON			
★	Reserved	OFF			
	Reserved		ON		
★	Reserved		OFF		
	MDB Mode			OFF	OFF
	JPSTD Dummy Mode			OFF	ON
★	MDB Dummy Mode	(Note.5)		ON	OFF
	ICT-BC Mode			ON	ON

★ Manufacture setting

Currency Assign Data

Interface / Bill value	JPSTD Dummy	ICT-BC	MDB (Dummy)	Recycler banknote inventory	
BV1	THB 20	THB 20	THB 20	THB 20	35 pcs
BV2	THB 50	THB 50	THB 50	THB 50	35 pcs
BV3	THB 100	THB 100	THB 100	THB 100	30 pcs
BV4	THB 500	THB 500	THB 500	THB 500	30 pcs

© 2021 International Currency Technologies Corporation
V. 4.0 Part Number : SWDTTH40400-R