

BRV-VND7

BRV Option Switch Settings: 1(ICT-BC/MDB/JPSTD Dummy/MDB Dummy)

Supported bill VND 1000, 2000, 5000, 10000, 20000. 50000, 100000 7bills.

BRV dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject VND 1000 & 2000	ON											
★ Accept VND 1000 & 2000	OFF											
★ Reject VND 5000 & 10000		ON										
★ Accept VND 5000 & 10000		OFF										
★ Reject VND 20000 & 50000			ON									
★ Accept VND 20000 & 50000			OFF									
★ Reject VND 100000				ON								
★ Accept VND 100000				OFF								
★ Standard Anti-Fish Security					ON							
★ High Anti-Fish Security					OFF							
★ Normal						OFF	OFF					
★ Load Banknote to Recycle						ON	OFF					
★ Disable Recycler Funtion						OFF	ON					
★ Unload Banknote to Stacker						ON	ON					
★ High Acceptance (Note.4)								ON				
★ Standard Acceptance								OFF				
MDB Mode	MDB Dummy Mode		SW1	SW2	SW3	SW4	JPSTD Dummy Mode					
★ Reserved	Reserved		ON				★ 255 Bank Note Limitation Per Transaction	ON	ON	ON		
★ Reserved	Reserved		OFF				1 Bank Note Limitation Per Transaction	OFF	OFF	OFF		
★ Reserved	Reserved			ON			2 Bank Note Limitation Per Transaction	ON	OFF	OFF		
★ Reserved	Reserved			OFF			3 Bank Note Limitation Per Transaction	OFF	ON	OFF		
★ Reserved	Reserved				ON		4 Bank Note Limitation Per Transaction	ON	ON	OFF		
★ Reserved	Reserved				OFF		5 Bank Note Limitation Per Transaction	OFF	OFF	ON		
★ Reserved	Reserved					ON	6 Bank Note Limitation Per Transaction	ON	OFF	ON		
★ Reserved	Reserved					OFF	7 Bank Note Limitation Per Transaction	OFF	ON	ON		
★ Virtual MDB (Note.5) Recycler Function	No Refund After the Deal				ON		No Refund After the Deal					ON
★ Standard MDB Recycler Function	★ Refund After the Deal				OFF		★ Refund After the Deal					OFF

★ Manufacture setting

- Note : (1) After setting dip switch of the credit pulses,you should reset the bill acceptor again.
 (2) Please reset the bill acceptor after set the dip switch.
 (3) calibrate card is needed.
 (4) High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.
 (5) Recycked Banknote represents virtual MDB coin type.
 (6) Normal:Scaling Factor (SF) = 1 : Decimal Point Position (DPP) = 0
 (7) The function(credit divide by1000) is used at standard MDB recycler mode.
 (8) The function(credit divide by100) is used at standard MDB recycler mode.
 (9) The credit divide by 100 on JPSTD Dummy Mode.

BRV-VND7(ICT-BC/MDB/JPSTD Dummy/MDB Dummy)

Interface Settings: 2(ICT-BC)

INTERFACE	SW5	SW6	SW7	SW8
Reserved	ON			
★ Reserved	OFF			
Connect with MDB Connector		ON		
★ Connect with RS232 Connector		OFF		
MDB Mode			OFF	OFF
JPSTD Dummy Mode			OFF	ON
MDB Dummy Mode			ON	OFF
★ ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(JPSTD Dummy)

INTERFACE	SW5	SW6	SW7	SW8
Escrow (JPSTD Dummy Mode)	ON			
★ No Escrow (JPSTD Dummy Mode)	OFF			
No Bill Acceptor Error Code		ON		
★ Bill Acceptor Error Code		OFF		
MDB Mode			OFF	OFF
★ JPSTD Dummy Mode			OFF	ON
MDB Dummy Mode			ON	OFF
ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB)

INTERFACE	SW5	SW6	SW7	SW8
★ Normal Credit (Note.6)	OFF	OFF		
Credit divide by 1000 (Note.7)	OFF	ON		
Credit divide by 100 (Note.8)	ON	OFF		
Reserved	ON	ON		
★ MDB Mode			OFF	OFF
JPSTD Dummy Mode			OFF	ON
MDB Dummy Mode			ON	OFF
ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB Dummy)

INTERFACE	SW5	SW6	SW7	SW8
★ Normal Credit (Note.6)	OFF	OFF		
Credit divide by 1000 (Note.7)	OFF	ON		
Credit divide by 100 (Note.8)	ON	OFF		
Reserved	ON	ON		
MDB Mode			OFF	OFF
JPSTD Dummy Mode			OFF	ON
★ MDB Dummy Mode			ON	OFF
ICT-BC Mode			ON	ON

★ Manufacture setting

Currency Assign Data

Interface Bill value	JPSTD Dummy	ICT-BC	MDB (Dummy)			Recycler banknote inventory	
			Note.6	Note.7	Note.8		
BV1	VND 1000	VND 1000	VND 1000	VND 1	VND 10	VND 1000	35 pcs
BV2	VND 2000	VND 2000	VND 2000	VND 2	VND 20	VND 2000	35 pcs
BV3	VND 5000	VND 5000	VND 5000	VND 5	VND 50	VND 5000	35 pcs
BV4	VND 10000	VND 10000	VND 10000	VND 10	VND 100	VND 10000	35 pcs
BV5	VND 20000	VND 20000	VND 20000	VND 20	VND 200	VND 20000	35 pcs
BV6	VND 50000	VND 50000	VND 50000	VND 50	VND 500	VND 50000	35 pcs
BV7	VND 100000	VND 100000	VND 100000	VND 100	VND 1000	VND 100000	35 pcs