

BRV-XCD8(XCD+USD)

BRV Option Switch Settings: 1(ICT-BC/MDB/JPSTD Dummy)

Supported bill XCD 5, 10, 20, 50, 100 5bills. USD 1, 5, 10 3bills.

BRV dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject XCD 5	ON											
★ Accept XCD 5	OFF											
★ Reject XCD 10 & 20		ON										
★ Accept XCD 10 & 20		OFF										
★ Reject XCD 50 & 100			ON									
★ Accept XCD 50 & 100			OFF									
★ Reject USD 1				ON								
★ Accept USD 1				OFF								
★ Reject USD 5 & 10					ON							
★ Accept USD 5 & 10					OFF							
★ Normal						OFF	OFF					
★ Load Banknote to Recycle						ON	OFF					
★ Load Banknote to Stacker						OFF	ON					
★ Unload Banknote to Stacker						ON	ON					
★ Reserved								ON				
★ Reserved								OFF				
MDB Mode	SW1	SW2	SW3	SW4	JPSTD Dummy Mode							
★ Reserved	ON				★ 255 Bank Note Limitation Per Transaction	ON	ON	ON				
★ Reserved	OFF				1 Bank Note Limitation Per Transaction	OFF	OFF	OFF				
★ Reserved		ON			2 Bank Note Limitation Per Transaction	ON	OFF	OFF				
★ Reserved		OFF			3 Bank Note Limitation Per Transaction	OFF	ON	OFF				
★ Reserved			ON		4 Bank Note Limitation Per Transaction	ON	ON	OFF				
★ Reserved				ON	5 Bank Note Limitation Per Transaction	OFF	OFF	ON				
★ Reserved				OFF	6 Bank Note Limitation Per Transaction	ON	OFF	ON				
★ Reserved					7 Bank Note Limitation Per Transaction	OFF	ON	ON				
★ Virtual MDB Recycler Function (Note.4)				ON	No Refund After the Deal							ON
★ Standard MDB Recycler Function				OFF	★ Refund After the Deal							OFF

★ Manufacture setting

Note : (1) After setting dip switch of the credit pulses,you should reset the bill acceptor again.

(2) Please reset the bill acceptor after set the dip switch.

(3) Calibrate card is needed.

(4) Recycled Banknote represents virtual MDB coin type.

(5) 1 USD = 2.5 XCD

BRV-XCD8(ICT-BC/MDB/JPSTD Dummy)

Interface Settings: 2(ICT-BC)

Interface Settings: 2(JPSTD Dummy)

INTERFACE	SW5	SW6	SW7	SW8
Reserved	ON			
★ Reserved	OFF			
★ Connect with MDB Connector		ON		
★ Connect with RS232 Connector		OFF		
★ MDB Mode			OFF	OFF
★ JPSTD Dummy Mode			OFF	ON
★ Reserved			ON	OFF
★ ICT-BC Mode			ON	ON

★ Manufacture setting

INTERFACE	SW5	SW6	SW7	SW8
★ Escrow (JPSTD Dummy Mode)	ON			
★ No Escrow (JPSTD Dummy Mode)	OFF			
★ Reserved		ON		
★ Reserved		OFF		
★ MDB Mode			OFF	OFF
★ JPSTD Dummy Mode			OFF	ON
★ Reserved			ON	OFF
★ ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB)

INTERFACE	SW5	SW6	SW7	SW8
★ Scaling Factor (SF)= 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF)= 10 Decimal Point Position (DPP) = 1	OFF			
★ Reserved		ON		
★ Reserved		OFF		
★ MDB Mode			OFF	OFF
★ JPSTD Dummy Mode			OFF	ON
★ Reserved			ON	OFF
★ ICT-BC Mode			ON	ON

★ Manufacture setting

Currency Assign Data

Interface Bill value	JPSTD Dummy	ICT-BC	MDB	Recycler banknote inventory	
BV1	XCD 5	XCD 5	XCD 5	XCD 5	35 pcs
BV2	XCD 10	XCD 10	XCD 10	XCD 10	35 pcs
BV3	XCD 20	XCD 20	XCD 20	XCD 20	35 pcs
BV4	XCD 50	XCD 50	XCD 50	XCD 50	35 pcs
BV5	XCD 100	XCD 100	XCD 100	XCD 100	35 pcs
BV6	USD 1	USD 1	USD 1	USD 1	30 pcs
BV7	USD 5	USD 5	USD 5	USD 5	30 pcs
BV8	USD 10	USD 10	USD 10	USD 10	30 pcs