

L77F/PL77-BYN6

L77F/PL77 DIP SWITCHES SETTING : 1(Pulse/MDB/CCNet/ICT104U)

Supported bill BYN 5, 10, 20, 50, 100, 200 6bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / BYN 5	OFF	OFF	OFF							
2 Pulses / BYN 5	OFF	OFF	ON							
3 Pulses / BYN 5	OFF	ON	OFF							
4 Pulses / BYN 5	OFF	ON	ON							
5 Pulses / BYN 5	ON	OFF	OFF							
10 Pulses / BYN 5	ON	OFF	ON							
20 Pulses / BYN 5	ON	ON	OFF							
50 Pulses / BYN 5	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
Inhibit level Active High					OFF					
★ Accept BYN 5 & 10						ON				
Reject BYN 5 & 10						OFF				
★ Accept BYN 20							ON			
Reject BYN 20							OFF			
★ Accept BYN 50								ON		
Reject BYN 50								OFF		
★ Accept BYN 100									ON	
Reject BYN 100									OFF	
★ Accept BYN 200										ON
Reject BYN 200										OFF

★ Manufacture setting

Note : (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

L77F/PL77-BYN6(Pulse/MDB/CCNet/ICT104U)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
CCNet Mode		OFF	OFF	
Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
CCNet Mode		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	OFF			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0				
Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
★ MDB Mode		ON	ON	
CCNet Mode		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U	CCNet
BV1	BYN 5	BYN 5	BYN 5	BYN 5
BV2	BYN 10	BYN 10	BYN 10	BYN 10
BV3	BYN 20	BYN 20	BYN 20	BYN 20
BV4	BYN 50	BYN 50	BYN 50	BYN 50
BV5	BYN 100	BYN 100	BYN 100	BYN 100
BV6	BYN 200	BYN 200	BYN 200	BYN 200

DIP SWITCHES SETTING : 2(CCNet)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
★ CCNet Mode		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting