

L77F/PL77-BYN6

L77F/PL77-P3/P6 DIP SWITCHES SETTING : 1(Pulse/RS232 A0)

Supported bill Br 5, 10, 20, 50, 100, 200 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / Br 5	OFF	OFF	OFF							
	2 Pulses / Br 5	OFF	OFF	ON							
	3 Pulses / Br 5	OFF	ON	OFF							
	4 Pulses / Br 5	OFF	ON	ON							
	5 Pulses / Br 5	ON	OFF	OFF							
	10 Pulses / Br 5	ON	OFF	ON							
	20 Pulses / Br 5	ON	ON	OFF							
	50 Pulses / Br 5	ON	ON	ON							
	Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★	Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept Br 5 & 10					ON					
	Reject Br 5 & 10					OFF					
★	Accept Br 20						ON				
	Reject Br 20						OFF				
★	Accept Br 50							ON			
	Reject Br 50							OFF			
★	Accept Br 100								ON		
	Reject Br 100								OFF		
★	Accept Br 200									ON	
	Reject Br 200									OFF	

★ Manufacture setting

Note:(1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

L77F/PL77-BYR6(Pulse/RS232 A0)

DIP SWITCHES SETTING : 2(Pulse)

Currency Assign Data

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	RS232 A0 Interface Mode		OFF		
	Reserved			ON	
★				OFF	
	Reserved				ON
★					OFF

★ Manufacture setting

Interface Bill value	RS232 A0	Pulse
BV1	Br 5	Br 5
BV2	Br 10	Br 10
BV3	Br 20	Br 20
BV4	Br 50	Br 50
BV5	Br 100	Br 100
BV6	Br 200	Br 200

DIP SWITCHES SETTING : 2(RS232 A0)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	Pulse Mode		ON		
★	RS232 A0 Interface Mode		OFF		
	Reserved			ON	
★				OFF	
	Reserved				ON
★					OFF

★ Manufacture setting

RS232 A0 INFORMATION

BillType Data	
Code	Denomination
1	Reserved
2	Br 5
3	Br 10
4	Br 20
5	Br 50
6	Br 100
7	Br 200