

# L77F/PL77-GMD5

## L77F/PL77 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/MDB)

Supported bill GMD 10, 20, 50, 100, 200 5bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / GMD 10	OFF	OFF	OFF							
2 Pulses / GMD 10	OFF	OFF	ON							
3 Pulses / GMD 10	OFF	ON	OFF							
4 Pulses / GMD 10	OFF	ON	ON							
5 Pulses / GMD 10	ON	OFF	OFF							
10 Pulses / GMD 10	ON	OFF	ON							
20 Pulses / GMD 10	ON	ON	OFF							
100 Pulses / GMD 10	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept GMD 10						ON				
Reject GMD 10						OFF				
★ Accept GMD 20							ON			
Reject GMD 20							OFF			
★ Accept GMD 50								ON		
Reject GMD 50								OFF		
★ Accept GMD 100									ON	
Reject GMD 100									OFF	
★ Accept GMD 200										ON
Reject GMD 200										OFF

★ Manufacture setting

Note : (1) Please reset the bill acceptor after set the dip switch.  
(2) Dip Switch 1 to 5 are only for Pulse mode.

# L77F/PL77-GMD5(Pulse/ICT104U/ICT104V/MDB)

## DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

## DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

## DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
★ MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

## Currency Assign Data

Interface Bill value	Pulse	ICT104U	MDB	ICT104V
BV1	GMD 10	GMD 10	GMD 10	GMD 10
BV2	GMD 20	GMD 20	GMD 20	GMD 20
BV3	GMD 50	GMD 50	GMD 50	GMD 50
BV4	GMD 100	GMD 100	GMD 100	GMD 100
BV5	GMD 200	GMD 200	GMD 200	GMD 200

## DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
★ ICT104V Mode		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting