

L77F/PL77-WST5

L77T DIP SWITCHES SETTING : 1(Pulse/RS232 A0/V2.2)

Supported bill THB 5, 10, 20, 50, 100 5bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / WST 5	OFF	OFF	OFF							
2 Pulses / WST 5	OFF	OFF	ON							
3 Pulses / WST 5	OFF	ON	OFF							
4 Pulses / WST 5	OFF	ON	ON							
5 Pulses / WST 5	ON	OFF	OFF							
10 Pulses / WST 5	ON	OFF	ON							
20 Pulses / WST 5	ON	ON	OFF							
100 Pulses / WST 5	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept WST 5						ON				
Reject WST 5						OFF				
★ Accept WST 10							ON			
Reject WST 10							OFF			
★ Accept WST 20								ON		
Reject WST 20								OFF		
★ Accept WST 50									ON	
Reject WST 50									OFF	
★ Accept WST 100										ON
Reject WST 100										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip Switch 1 to 5 are only for Pulse mode.

Currency Assign Data

Interface Bill value	Pulse	RS232 A0	V2.2
BV1	WST 5	WST 5	WST 5
BV2	WST 10	WST 10	WST 10
BV3	WST 20	WST 20	WST 20
BV4	WST 50	WST 50	WST 50
BV5	WST 100	WST 100	WST 100

L77F/PL77/-WST5(Pulse/RS232 A0/V2.2)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
RS232 A0 Mode		ON	ON	
V2.2 Mode		OFF	ON	
Reserved		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(RS232 A0)

FUNCTION	SW1	SW2	SW3	SW4	RS232 A0 INFORMATION
★ Reserved	ON				
	OFF				Code Denomination
Pulse Mode		ON	OFF		1 Reserved
★ RS232 A0 Mode		ON	ON		2 Reserved
V2.2 Mode		OFF	ON		3 WST 5
Reserved		OFF	OFF		4 WST 10
Reserved				ON	5 WST 20
★ Reserved				OFF	6 WST 50
					7 WST 100
					8 Reserved
					9 Reserved

★ Manufacture setting

DIP SWITCHES SETTING : 2(V2.2)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
RS232 A0 Mode		ON	ON	
★ V2.2 Mode		OFF	ON	
Reserved		OFF	OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting