

DOP7

L83 DIP SWITCHES SETTING : 1(Pulse/ccTalk/Parallel A5)

Supported bill RD\$ 10, 20, 50, 100, 200, 500, 1000
7 bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / RD\$ 10	OFF	OFF	OFF							
2 Pulse / RD\$ 10	OFF	OFF	ON							
3 Pulse / RD\$ 10	OFF	ON	OFF							
4 Pulse / RD\$ 10	OFF	ON	ON							
5 Pulse / RD\$ 10	ON	OFF	OFF							
10 Pulse / RD\$ 10	ON	OFF	ON							
20 Pulse / RD\$ 10	ON	ON	OFF							
100 Pulse / RD\$ 10	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
Inhibit level Active High					OFF					
★ Accept RD\$ 10 & 20						ON				
Reject RD\$ 10 & 20						OFF				
★ Accept RD\$ 50 & 100							ON			
Reject RD\$ 50 & 100							OFF			
★ Accept RD\$ 200								ON		
Reject RD\$ 200								OFF		
★ Accept RD\$ 500									ON	
Reject RD\$ 500									OFF	
★ Accept RD\$ 1000										ON
Reject RD\$ 1000										OFF

★ Manufacture setting

Note:(1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

L83-DOP7(Pulse/ccTalk/Parallel A5)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ccTalk)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
★ ccTalk Interface		OFF	OFF	
ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Note: Turn this dip to with restart the bill acceptor will restore

CCTalk address to its default value of 40 and the encryption key to its default value of 123456.

DIP SWITCHES SETTING : 2(Parallel A5)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
★ Parallel A5 Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting