

L83-KES5

L83 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/ MDB)

Supported bill KES 50, 100, 200, 500, 1000 5 bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / KES 50	OFF	OFF	OFF							
2 Pulses / KES 50	OFF	OFF	ON							
3 Pulses / KES 50	OFF	ON	OFF							
4 Pulses / KES 50	OFF	ON	ON							
5 Pulses / KES 50	ON	OFF	OFF							
10 Pulses / KES 50	ON	OFF	ON							
20 Pulses / KES 50	ON	ON	OFF							
100 Pulses / KES 50	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept KES 50						ON				
Reject KES 50						OFF				
★ Accept KES 100							ON			
Reject KES 100							OFF			
★ Accept KES 200								ON		
Reject KES 200								OFF		
★ Accept KES 500									ON	
Reject KES 500									OFF	
★ Accept KES 1000										ON
Reject KES 1000										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.
(2) Dip switches 1 to 5 are only used for pulse protocol.

L83-KES5(Pulse/ICT104U/ICT104V/ MDB)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U	ICT104V
BV1	KES 50	KES 50	KES 50	KES 50
BV2	KES 100	KES 100	KES 100	KES 100
BV3	KES 200	KES 200	KES 200	KES 200
BV4	KES 500	KES 500	KES 500	KES 500
BV5	KES 1000	KES 1000	KES 1000	KES 1000

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
★ ICT104V Mode		OFF	OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting