

V7P-AMD7

V7P Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill AMD 1000, 2000, 5000, 10000, 20000, 50000, 100000 7bills.

V7P dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject AMD 1000 & 2000	ON											
★ Accept AMD 1000 & 2000	OFF											
★ Reject AMD 5000 & 10000		ON										
★ Accept AMD 5000 & 10000		OFF										
★ Reject AMD 20000			ON									
★ Accept AMD 20000			OFF									
★ Reject AMD 50000				ON								
★ Accept AMD 50000				OFF								
★ Reject AMD 100000					ON							
★ Accept AMD 100000					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / AMD 1000									OFF	OFF		
★ 2 pulses / AMD 1000									ON	OFF		
★ 4 pulses / AMD 1000									OFF	ON		
★ 20 pulses / AMD 1000									ON	ON		
★ Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
	60ms LO / 300ms HI								ON	OFF		
	30ms LO / 50ms HI								OFF	ON		
	150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

◆ Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

V7P-AMD7(Pulse/ICT104V/ICT104U/MDB)

Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Settings: 2(ICT104U)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
★ MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	ICT104V	Pulse	MDB
★ BV1	AMD 1000	AMD 1000	AMD 1000	AMD 1000
★ BV2	AMD 2000	AMD 2000	AMD 2000	AMD 2000
★ BV3	AMD 5000	AMD 5000	AMD 5000	AMD 5000
★ BV4	AMD 10000	AMD 10000	AMD 10000	AMD 10000
★ BV5	AMD 20000	AMD 20000	AMD 20000	AMD 20000
★ BV6	AMD 50000	AMD 50000	AMD 50000	AMD 50000
★ BV7	AMD100000	AMD100000	AMD100000	AMD100000

Interface Settings: 2(ICT104V)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
★ ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting