

V7P-CAD5

V7P Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill CAD 5, 10, 20, 50, 100 5bills.

V7P dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject CAD 5	ON											
★ Accept CAD 5	OFF											
★ Reject CAD 10		ON										
★ Accept CAD 10		OFF										
★ Reject CAD 20			ON									
★ Accept CAD 20			OFF									
★ Reject CAD 50				ON								
★ Accept CAD 50				OFF								
★ Reject CAD 100					ON							
★ Accept CAD 100					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ Pulse Mode												
★ 1 pulse / CAD 1									OFF	OFF		
★ 2 pulses / CAD 1									ON	OFF		
★ 4 pulses / CAD 1									OFF	ON		
★ 20 pulses / CAD 1									ON	ON		
★ Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
	60ms LO / 300ms HI								ON	OFF		
	30ms LO / 50ms HI								OFF	ON		
	150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

Note :

- 1.Default setting.
- 2.Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.
- 3.Remove the front cover and the dip-switch in on the CPU board.

V7P-CAD5(Pulse/ICT104V/ICT104U/MDB)

Interface Settings: 2(Pulse) Currency Assign Data

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved			ON	
			OFF	

★ Manufacture setting

Interface Bill value	Pulse	MDB	ICT104U	ICT104V
BV1	CAD 5	CAD 5	CAD 5	CAD 5
BV2	CAD 10	CAD 10	CAD 10	CAD 10
BV3	CAD 20	CAD 20	CAD 20	CAD 20
BV4	CAD 50	CAD 50	CAD 50	CAD 50
BV5	CAD100	CAD100	CAD100	CAD100

Interface Settings: 2(ICT104U)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved			ON	
			OFF	

★ Manufacture setting

Interface Settings: 2(ICT104V)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved			ON	
			OFF	

★ Manufacture setting

Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100	ON			
Decimal Point Position (DPP) = 2				
Scaling Factor (SF) = 1	OFF			
Decimal Point Position (DPP) = 0				
Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
★ MDB Mode		ON	ON	
★ Reserved			ON	
			OFF	

★ Manufacture setting