

V7P-RUB6

V7P Option Switch Settings: 1(Pulse/ICT104/ICT104U/MDB)

Supported bill Ruble 50, 100, 200, 500, 1000, 2000 6bills.

V7P dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject Ruble 50	ON											
★ Accept Ruble 50	OFF											
★ Reject Ruble 100		ON										
★ Accept Ruble 100		OFF										
★ Reject Ruble 200			ON									
★ Accept Ruble 200			OFF									
★ Reject Ruble 500				ON								
★ Accept Ruble 500				OFF								
★ Reject Ruble 1000 & 2000					ON							
★ Accept Ruble 1000 & 2000					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / Ruble 50									OFF	OFF		
★ 5 pulses / Ruble 50									ON	OFF		
★ 10 pulses / Ruble 50									OFF	ON		
★ 50 pulses / Ruble 50									ON	ON		
★ Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
	60ms LO / 300ms HI								ON	OFF		
	30ms LO / 50ms HI								OFF	ON		
	150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

◆ Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

(Please refer to "SW1" setting.)

V7P-RUB6(Pulse/ICT104/ICT104U/MDB)

Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ICT104 Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	ICT104	MDB	Pulse
BV1				
BV2	Ruble 50	Ruble 50	Ruble 50	Ruble 50
BV3	Ruble 100	Ruble 100	Ruble 100	Ruble 100
BV4	Ruble 500	Ruble 500	Ruble 500	Ruble 500
BV5	Ruble 1000	Ruble 1000	Ruble 1000	Ruble 1000
BV6	Ruble 200	Ruble 200	Ruble 200	Ruble 200
BV7	Ruble 2000	Ruble 2000	Ruble 2000	Ruble 2000

Interface Settings: 2(ICT104U)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
ICT104 Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Settings: 2(ICT104)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
ICT104 Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100	ON			
Decimal Point Position (DPP) = 2	OFF			
Scaling Factor (SF) = 1				
Decimal Point Position (DPP) = 0				
Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ICT104 Mode		OFF	ON	
★ MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting