

V7P-SGD3

V7P Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill SGD 2, 5, 10 3bills.

V7P dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject SGD 2	ON											
★ Accept SGD 2	OFF											
★ Reject SGD 5		ON										
★ Accept SGD 5		OFF										
★ Reject SGD 10			ON									
★ Accept SGD 10			OFF									
★ Reserved				ON								
★ Reserved				OFF								
★ Reserved					ON							
★ Reserved					OFF							
★ Stack Banknote when Power-up						ON						
★ Reject Banknote when Power-up						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / SGD 1									OFF	OFF		
★ 5 pulses / SGD 1									ON	OFF		
★ 10 pulses / SGD 1									OFF	ON		
★ 25 pulses / SGD 1									ON	ON		
★ Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
	60ms LO / 300ms HI								ON	OFF		
	30ms LO / 50ms HI								OFF	ON		
	150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

◆ Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

(4) Scaling Factor (SF) = 10, Decimal Point Position (DPP) = 1, Country CODE = 0063

V7P-SGD3(Pulse/ICT104V/ICT104U/MDB)

Interface Settings: 2(Pulse) Currency Assign Data

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
★ ICT104V Mode		OFF	ON	
★ MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface	ICT104U	ICT104V	MDB	Pulse
★ Bill value				
★ BV1	SGD 2	SGD 2	SGD 2	SGD 2
★ BV2	SGD 5	SGD 5	SGD 5	SGD 5
★ BV3	SGD 10	SGD 10	SGD 10	SGD 10

Interface Settings: 2(ICT104U/ICT104V)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
★ Reserved	OFF			
★ Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
★ ICT104V Mode		OFF	ON	
★ MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
★ Reserved	OFF			
★ Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
★ ICT104V Mode		OFF	ON	
★ MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	OFF			
★ Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	ON			
	OFF			
★ Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
★ ICT104V Mode		OFF	ON	
★ MDB Mode		ON	ON	
★ Customized (Note.4)				ON
★ Standard				OFF

★ Manufacture setting

Note : (4) Scaling Factor (SF) = 10, Decimal Point Position (DPP) = 1, Country CODE = 0063