

V7P-TMT4

V7P Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill TMT 1, 5, 10, 20 4bills.

V7P dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject TMT 1	ON											
★ Accept TMT 1	OFF											
★ Reject TMT 5		ON										
★ Accept TMT 5		OFF										
★ Reject TMT 10			ON									
★ Accept TMT 10			OFF									
★ Reject TMT 20				ON								
★ Accept TMT 20				OFF								
★ Reserved					ON							
★ Reserved					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ Pulse Mode												
★ 1 pulse / TMT 1									OFF	OFF		
5 pulses / TMT 1									ON	OFF		
10 pulses / TMT 1									OFF	ON		
20 pulses / TMT 1									ON	ON		
★ Interface Timing Conversion											OFF	OFF
											ON	OFF
											OFF	ON
											ON	ON

★ Manufacture setting

Note :

1.Default setting.

2.Use 2nd and 3rd dip of the internal dip-switch to change different interface Protocol.

3.Remove the front cover and the dip-switch in on the CPU board.

V7P-TMT4(Pulse/ICT104V/ICT104U/MDB)

Interface Settings: 2(Pulse)

Currency Assign Data

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Bill value	Pulse	MDB	ICT104V	ICT104U
BV1	TMT 1	TMT 1	TMT 1	TMT 1
BV2	TMT 5	TMT 5	TMT 5	TMT 5
BV3	TMT 10	TMT 10	TMT 10	TMT 10
BV4	TMT 20	TMT 20	TMT 20	TMT 20

Interface Settings: 2(ICT104U)

Interface Settings: 2(ICT104V)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100	ON			
Decimal Point Position (DPP) = 2				
Scaling Factor (SF) = 1	OFF			
Decimal Point Position (DPP) = 0				
Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
★ MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting