

# V7P-TWD4

## V7P Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill TWD 100, 200, 500, 1000 4bills.

V7P dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject TWD 100	ON											
★ Accept TWD 100	OFF											
★ Reject TWD 200		ON										
★ Accept TWD 200		OFF										
★ Reject TWD 500			ON									
★ Accept TWD 500			OFF									
★ Reject TWD 1000				ON								
★ Accept TWD 1000				OFF								
★ Reserved					ON							
★ Reserved					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ <b>Pulse Mode</b>												
★ 1 pulse / TWD 100								OFF	OFF			
★ 5 pulses / TWD 100								ON	OFF			
★ 10 pulses / TWD 100								OFF	ON			
★ 25 pulses / TWD 100								ON	ON			
★ Interface Timing Conversion										OFF	OFF	
		50ms LO / 50ms HI								ON	OFF	
		60ms LO / 300ms HI								OFF	ON	
		30ms LO / 50ms HI								ON	ON	
		150ms LO / 150ms HI								ON	ON	

★ Manufacture setting

Note :

1.Default setting.

2.Use 2nd and 3rd dip of the internal dip-switch to change different interface Protocol.

3.Remove the front cover and the dip-switch in on the CPU board.

# V7P-TWD4(Pulse/ICT104V/ICT104U/MDB)

## Interface Settings: 2(Pulse)

## Currency Assign Data

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Bill value	Pulse	MDB	ICT104V	ICT104U
BV1	TWD 100	TWD 100	TWD 100	TWD 100
BV2	TWD 200	TWD 200	TWD 200	TWD 200
BV3	TWD 500	TWD 500	TWD 500	TWD 500
BV4	TWD 1000	TWD 1000	TWD 1000	TWD 1000

## Interface Settings: 2(ICT104U)

## Interface Settings: 2(ICT104V)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

## Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
ICT104U Mode		OFF	OFF	
ICT104V Mode		OFF	ON	
★ MDB Mode		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting