

XBA mini-AUD5

XBA mini Option Switch Settings: 1(Pulse/MDB/ICT104V/ICT104U)

Supported bill AUD 5, 10, 20, 50, 100 5bills.

XBA mini dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject AUD 5	ON											
★ Accept AUD 5	OFF											
★ Reject AUD 10		ON										
★ Accept AUD 10		OFF										
★ Reject AUD 20			ON									
★ Accept AUD 20			OFF									
★ Reject AUD 50				ON								
★ Accept AUD 50				OFF								
★ Reject AUD 100					ON							
★ Accept AUD 100					OFF							
★ Disable Bill Reject 4 Times BA Stop By 30 Sec						ON						
★ Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF						
★ Stack Banknote when Power-up							ON					
★ Reject Banknote when Power-up							OFF					
★ High Acceptance (Note.2)								ON				
★ High Security								OFF				
★ Inhibit Active High									ON			
★ Inhibit Active Low									OFF			
★ Turn OFF bezel LED										ON		
★ Turn ON bezel LED										OFF		
★ Interface Timing Conversion	50ms LO / 50ms HI									OFF	OFF	
	60ms LO / 300ms HI									ON	OFF	
	30ms LO / 50ms HI									OFF	ON	
	150ms LO / 150ms HI									ON	ON	

★ Manufacture setting

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note : (1) Calibration card is needed.

(2) High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

XBA mini-AUD5(Pulse/MDB/ICT104V/ICT104U)

Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
Other Mode		OFF		
★ 1 pulse / AUD 5			OFF	OFF
5 pulses / AUD 5			OFF	ON
10 pulses / AUD 5			ON	OFF
20 pulses / AUD 5			ON	ON

★ Manufacture setting

Interface Settings: 2(ICT104V)

INTERFACE	SW1	SW2	SW3	SW4
★ Connect with coin changer	ON			
Connect with ICT JPSTD converter board	OFF			
★ Pulse Mode		ON		
Other Mode		OFF		
MDB Mode			OFF	OFF
Reserved			OFF	ON
ICT104U Mode			ON	OFF
★ ICT104V Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON		
Other Mode		OFF		
★ MDB Mode			OFF	OFF
Reserved			OFF	ON
ICT104U Mode			ON	OFF
ICT104V Mode			ON	ON

★ Manufacture setting

Currency Assign Data

Interface	ICT104U	ICT104V	Pulse	MDB
★ Bill value				
BV1	AUD 5	AUD 5	AUD 5	AUD 5
BV2	AUD 10	AUD 10	AUD 10	AUD 10
BV3	AUD 20	AUD 20	AUD 20	AUD 20
BV4	AUD 50	AUD 50	AUD 50	AUD 50
BV5	AUD 100	AUD 100	AUD 100	AUD 100

Interface Settings: 2(Other)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON		
Other Mode		OFF		
MDB Mode			OFF	OFF
Reserved			OFF	ON
ICT104U Mode			ON	OFF
ICT104V Mode			ON	ON

★ Manufacture setting