

## XBA mini-MYR6

### XBA mini Option Switch Settings: 1(Pulse/MDB/ICT104V/ICT104U)

Supported bill M\$ 1, 5, 10, 20, 50, 100 6bills.

XBA mini dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject M\$ 1	ON											
★ Accept M\$ 1	OFF											
★ Reject M\$ 5		ON										
★ Accept M\$ 5		OFF										
★ Reject M\$ 10			ON									
★ Accept M\$ 10			OFF									
★ Reject M\$ 20				ON								
★ Accept M\$ 20				OFF								
★ Reject M\$ 50 & 100					ON							
★ Accept M\$ 50 & 100					OFF							
★ Disable Bill Reject 4 Times BA Stop By 30 Sec						ON						
★ Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF						
★ Stack Banknote when Power-up							ON					
★ Reject Banknote when Power-up							OFF					
★ Reserved								ON				
★ Reserved								OFF				
★ Inhibit Active High									ON			
★ Inhibit Active Low										OFF		
★ MDB Special Mode	(No Error Code) (MDB Only)									ON		
★ MDB Normal Mode										OFF		
★ Interface Timing Conversion	50ms LO / 50ms HI										OFF	OFF
	60ms LO / 300ms HI										ON	OFF
	30ms LO / 50ms HI										OFF	ON
	150ms LO / 150ms HI										ON	ON

★ Manufacture setting

After setting dip switch of the credit pulses, you should reset the bill acceptor again

Note : (1) Calibrate card is needed.

## XBA mini-MYR6(Pulse/MDB/ICT104V/ICT104U)

### Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
Other Mode		OFF		
★ 1 pulse / M\$ 1			OFF	OFF
2 pulses / M\$ 1			OFF	ON
5 pulses / M\$ 1			ON	OFF
10 pulses / M\$ 1			ON	ON

★ Manufacture setting

### Interface Settings: 2(ICT104V)

INTERFACE	SW1	SW2	SW3	SW4
★ Connect with coin changer	ON			
Connect with ICT JPSTD Converter board	OFF			
Pulse Mode		ON		
Other Mode		OFF		
MDB Mode			OFF	OFF
Reserved			OFF	ON
ICT104U Mode			ON	OFF
★ ICT104V Mode			ON	ON

★ Manufacture setting

### Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON		
Other Mode		OFF		
★ MDB Mode			OFF	OFF
Reserved			OFF	ON
ICT104U Mode			ON	OFF
ICT104V Mode			ON	ON

★ Manufacture setting

### Currency Assign Data

Interface Bill value	ICT104U	ICT104V	Pulse	MDB
BV1	M\$ 1	M\$ 1	M\$ 1	M\$ 1
BV2				
BV3	M\$ 5	M\$ 5	M\$ 5	M\$ 5
BV4	M\$ 10	M\$ 10	M\$ 10	M\$ 10
BV5	M\$ 50	M\$ 50	M\$ 50	M\$ 50
BV6	M\$ 100	M\$ 100	M\$ 100	M\$ 100
BV7	M\$ 20	M\$ 20	M\$ 20	M\$ 20

### Interface Settings: 2(Other)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON		
Other Mode		OFF		
MDB Mode			OFF	OFF
Reserved			OFF	ON
ICT104U Mode			ON	OFF
★ ICT104V Mode			ON	ON

★ Manufacture setting