

## XBA mini-TWD4

### XBA mini Option Switch Settings: 1(Pulse/MDB/ICT104V/ICT104U)

Supported bill TWD 100, 200, 500, 1000 4bills.

XBA mini dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject TWD 100	ON											
★ Accept TWD 100	OFF											
★ Reject TWD 200		ON										
★ Accept TWD 200		OFF										
★ Reject TWD 500			ON									
★ Accept TWD 500			OFF									
★ Reject TWD 1000				ON								
★ Accept TWD 1000				OFF								
Reserved					ON							
★ Reserved					OFF							
★ Disable Bill Reject 4 Times BA Stop By 30 Sec						ON						
★ Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF						
★ Stack Banknote when Power-up							ON					
★ Reject Banknote when Power-up							OFF					
★ MDB special mode								ON				
★ Normal mode								OFF				
★ Inhibit Active High									ON			
★ Inhibit Active Low									OFF			
★ Reserved									ON			
★ Reserved									OFF			
★ Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
	60ms LO / 300ms HI								ON	OFF		
	30ms LO / 50ms HI								OFF	ON		
	150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

Note : (1) After setting dip switch of the credit pulses,you should reset the bill acceptor again.  
(2) Calibration card is needed.

## XBA mini-TWD4(Pulse/MDB/ICT104V/ICT104U)

### Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	1 pulse / TWD100			OFF	OFF
	5 pulses / TWD100			OFF	ON
	10 pulses / TWD100			ON	OFF
	25 pulses / TWD100			ON	ON

★ Manufacture setting

### Interface Settings: 2(ICT104V)

	INTERFACE	SW1	SW2	SW3	SW4
★	Connect with coin changer	ON			
	Connect with ICT JPSTD converter board	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB Mode			OFF	OFF
	Reserved			OFF	ON
	ICT104U Mode			ON	OFF
★	ICT104V Mode			ON	ON

★ Manufacture setting

### Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
★	MDB Mode			OFF	OFF
	Reserved			OFF	ON
	ICT104U Mode			ON	OFF
	ICT104V Mode			ON	ON

★ Manufacture setting

### Currency Assign Data

Interface	ICT104U	ICT104V	Pulse	MDB
Bill value				
BV1	TWD 100	TWD 100	TWD 100	TWD 100
BV2	TWD 200	TWD 200	TWD 200	TWD 200
BV3	TWD 500	TWD 500	TWD 500	TWD 500
BV4	TWD 1000	TWD 1000	TWD 1000	TWD 1000

### Interface Settings: 2(other)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB Mode			OFF	OFF
	Reserved			OFF	ON
	ICT104U Mode			ON	OFF
	ICT104V Mode			ON	ON

★ Manufacture setting