

A6-AUD4

A6 Option Switch Settings: 1

Supported bill \$A 5, 10, 20, 50 4bills.

A6 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject \$A 5	ON											
★ Accept \$A 5	OFF											
★ Reject \$A 10		ON										
★ Accept \$A 10		OFF										
★ Reject \$A 20			ON									
★ Accept \$A 20			OFF									
★ Reject \$A 50				ON								
★ Accept \$A 50				OFF								
★ Reserved					ON							
★ Reserved					OFF							
★ High Acceptance (Note.3)						ON						
★ High Security						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / \$A 5									OFF	OFF		
★ 5 pulses / \$A 5									ON	OFF		
★ 10 pulses / \$A 5									OFF	ON		
★ 20 pulses / \$A 5									ON	ON		
★ Interface Timing Conversion	50ms LO / 50ms HI										OFF	OFF
	60ms LO / 300ms HI										ON	OFF
	30ms LO / 50ms HI										OFF	ON
	150ms LO / 150ms HI										ON	ON

★ Manufacture setting

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

(3) High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

A6-AUD4 (PULSE/ICT002)

A6 Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
★ ICT002 Interface		OFF		
★ Reserved			ON	
			OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

A6 Interface Settings: 2(ICT002)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
★ Pulse Mode		ON		
★ ICT002 Interface		OFF		
★ Reserved			ON	
			OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT002
BV1	\$A 5	\$A 5
BV2	\$A 10	\$A 10
BV3	\$A 20	\$A 20
BV4	\$A 50	\$A 50