

A6-AUD4

A6 Option Switch Settings: 1

Supported bill \$A 5, 10, 20, 50 4bills.

A6 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4	
★ Reject \$A 5	ON												
★ Accept \$A 5	OFF												
★ Reject \$A 10		ON											
★ Accept \$A 10		OFF											
★ Reject \$A 20			ON										
★ Accept \$A 20			OFF										
★ Reject \$A 50				ON									
★ Accept \$A 50				OFF									
★ Reserved				ON									
★ Reserved				OFF									
★ High Acceptance (Note.3)					ON								
★ High Security					OFF								
★ Harness Disable						ON							
★ Harness Enable						OFF							
★ Inhibit Active High							ON						
★ Inhibit Active Low							OFF						
★ 1 pulse / \$A 5	1 pulse / \$A 5	(Note.4)						OFF	OFF				
★ 3 pulses / \$A 5	5 pulses / \$A 5	(Note.4)						ON	OFF				
★ 5 pulses / \$A 5	10 pulses / \$A 5	(Note.4)						OFF	ON				
★ 6 pulses / \$A 5	20 pulses / \$A 5	(Note.4)						ON	ON				
★ Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF			
	60ms LO / 300ms HI								ON	OFF			
	30ms LO / 50ms HI								OFF	ON			
	150ms LO / 150ms HI								ON	ON			

★ Manufacture setting

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

(3) High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

(4) Special pulse:When DIP-SW4 is ON,AUD 5=1 pulse,or 3 pulse,or 5 pulse,or 6 pulse.

Normal pulse:When DIP-SW4 is OFF,AUD 5=1 pulse,or 5 pulse,or 10 pulse,or 20 pulse.

A6-AUD4(Special PULSE/ICT002)

A6 Light Interface Settings: 2 (Pulse)

Currency Assign Data

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
★ Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
★ ICT002 Interface		OFF		
★ Reserved			ON	
★ Reserved			OFF	
★ Special pulse (Note 4)				ON
★ Normal pulse (Note 4)				OFF

★ Manufacture setting

Note.4. Special pulse:When DIP-SW4 is ON,AUD 5=1 pulse,or 3 pulse,or 5 pulse,or 6 pulse.

Normal pulse:When DIP-SW4 is OFF,AUD 5=1 pulse,or 5 pulse,or 10 pulse,or 20 pulse.

Interface Bill value	Pulse	ICT002
BV1	\$A 5	\$A 5
BV2	\$A 10	\$A 10
BV3	\$A 20	\$A 20
BV4	\$A 50	\$A 50

A6 Light Interface Settings: 2 (ICT002)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
★ Pulse Mode		ON		
★ ICT002 Interface		OFF		
★ Reserved			ON	
			OFF	
★ Reserved				ON
				OFF

★ Manufacture setting