

L70+/L70F-IDR4

L70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/MDB/ICT104V)

Supported bill IDR 10000, 20000, 50000, 100000 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10	
★	1 Pulse / IDR 10000	OFF	OFF	OFF								
	2 Pulses / IDR 10000	OFF	OFF	ON								
	3 Pulses / IDR 10000	OFF	ON	OFF								
	4 Pulses / IDR 10000	OFF	ON	ON								
	5 Pulses / IDR 10000	ON	OFF	OFF								
	10 Pulses / IDR 10000	ON	OFF	ON								
	20 Pulses / IDR 10000	ON	ON	OFF								
	100 Pulses / IDR 10000	ON	ON	ON								
★	Fast output Pulse Lo= 50ms Hi=100ms				ON							
	Slow output Pulse Lo= 50ms Hi=300ms				OFF							
★	Inhibit level Active Low					ON						
	Inhibit level Active High					OFF						
★	Accept IDR 10000						ON					
	Reject IDR 10000						OFF					
★	Accept IDR 20000							ON				
	Reject IDR 20000							OFF				
★	Accept IDR 50000									ON		
	Reject IDR 50000									OFF		
★	Accept IDR 100000										ON	
	Reject IDR 100000										OFF	
★	High Security											ON
	High Acceptance (Note.3)											OFF

★ Manufacture setting

Note:(1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

(4) The function(credit divide by1000) is only used at standard MDB recycler mode

(5) i .Special MDB setting mode works for vending machine. It can't accept

IDR 100,000 bill in this mode.

ii.The function(Normal credit/Credit divide) is disable when BA works at special MDB Setting Mode.

Appendix

L70+/L70F-IDR4(Pulse/ICT104U/MDB/ICT104V)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
	Credit-Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
	MDB Mode		ON	ON	
	ICT104V Interface		OFF	OFF	
	Disable Inverse Mode				ON
★	Enable Inverse Mode				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Interface		OFF	ON	
	MDB Mode		ON	ON	
	ICT104V Interface		OFF	OFF	
	Disable Inverse Mode				ON
★	Enable Inverse Mode				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	MDB	Pulse	ICT104U	ICT104V
BV1	IDR 10000	IDR 10000	IDR 10000	IDR 10000
BV2	IDR 20000	IDR 20000	IDR 20000	IDR 20000
BV3	IDR 50000	IDR 50000	IDR 50000	IDR 50000
BV4	IDR 100000	IDR 100000	IDR 100000	IDR 100000

DIP SWITCHES SETTING : 2(ICT104V)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
	MDB Mode		ON	ON	
★	ICT104V Interface		OFF	OFF	
	Disable Inverse Mode				ON
★	Enable Inverse Mode				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Normal credit	ON			
	Credit divide by 1000(MDB only) (Note.4)	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
★	MDB Mode		ON	ON	
	ICT104V Interface		OFF	OFF	
	Special MDB Setting(Base 5) (Note.5)				ON
★	Normal MDB Setting				OFF

★ Manufacture setting