

L70/L70F-ARS5

L70/L70F/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/MDB)

Supported bill ARS 500, 1000, 2000, 10000, 20000 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10			
★	1 Pulse / ARS 500	OFF	OFF	OFF										
	2 Pulses / ARS 500	OFF	OFF	ON										
	3 Pulses / ARS 500	OFF	ON	OFF										
	4 Pulses / ARS 500	OFF	ON	ON										
	5 Pulses / ARS 500	ON	OFF	OFF										
	10 Pulses / ARS 500	ON	OFF	ON										
	20 Pulses / ARS 500	ON	ON	OFF										
	100 Pulses / ARS 500	ON	ON	ON										
★	Fast output Pulse Lo= 50ms Hi=100ms				ON									
	Slow output Pulse Lo= 50ms Hi=300ms				OFF									
★	Inhibit level Active Low					ON								
	Inhibit level Active High					OFF								
★	Accept ARS 500						ON							
	Reject ARS 500						OFF							
★	Accept ARS 1000							ON						
	Reject ARS 1000							OFF						
★	Accept ARS 2000								ON					
	Reject ARS 2000								OFF					
★	Accept ARS 10000									ON				
	Reject ARS 10000									OFF				
★	Accept ARS 20000										ON			
	Reject ARS 20000										OFF			

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

L70/L70F-ARS5(Pulse/ICT104U/ICT104V/MDB)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	ON	
	MDB Mode		ON	ON	
	ICT104V Mode		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U	ICT104V
BV1	ARS 500	ARS 500	ARS 500	ARS 500
BV2	ARS 1000	ARS 1000	ARS 1000	ARS 1000
BV3	ARS 2000	ARS 2000	ARS 2000	ARS 2000
BV4	ARS 10000	ARS 10000	ARS 10000	ARS 10000
BV5	ARS 20000	ARS 20000	ARS 20000	ARS 20000

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	ON	
	MDB Mode		ON	ON	
	ICT104V Mode		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104V)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	ON	
	MDB Mode		ON	ON	
★	ICT104V Mode		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	ON	
★	MDB Mode		ON	ON	
	ICT104V Mode		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting