

L70/L70F-RUB7

L70/L70F/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/MDB)

Supported bill RUB 5, 10, 50, 100, 200, 500, 1000 7bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / RUB 5 _(Note.3) & 10	OFF	OFF	OFF							
2 Pulses / RUB 5 _(Note.3) & 10	OFF	OFF	ON							
3 Pulses / RUB 5 _(Note.3) & 10	OFF	ON	OFF							
4 Pulses / RUB 5 _(Note.3) & 10	OFF	ON	ON							
5 Pulses / RUB 5 _(Note.3) & 10	ON	OFF	OFF							
10 Pulses / RUB 5 _(Note.3) & 10	ON	OFF	ON							
20 Pulses / RUB 5 _(Note.3) & 10	ON	ON	OFF							
100 Pulses / RUB 5 _(Note.3) & 10	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept RUB 5(RUB 5=1 Pulse) (Note.3)					ON					
Reject RUB 5(RUB 10=1 Pulse)					OFF					
★ Accept RUB 10						ON				
Reject RUB 10						OFF				
★ Accept RUB 50 & 100							ON			
Reject RUB 50 & 100							OFF			
★ Accept RUB 200								ON		
Reject RUB 200								OFF		
★ Accept RUB 500 & 1000									ON	
Reject RUB 500 & 1000									OFF	

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) In Pulse mode :

if SW1 Dip6 is ON , 1 Pulse=RUB 5

if SW1 Dip6 is OFF, 1 Pulse=RUB 10

L70/L70F-RUB7(Pulse/ICT104U/ICT104V/MDB)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-PulseNormal High	ON			
Credit-Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
★ MDB Mode		ON	ON	
ICT104V Interface		OFF	OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting

Currency Assign Data

Interface	Pulse	MDB	ICT104U	ICT104V
Bill value				
BV1	RUB 10	RUB 10	RUB 10	RUB 10
BV2	RUB 50	RUB 50	RUB 50	RUB 50
BV3	RUB 100	RUB 100	RUB 100	RUB 100
BV4	RUB 500	RUB 500	RUB 500	RUB 500
BV5	RUB 1000	RUB 1000	RUB 1000	RUB 1000
BV6	Reserved	Reserved	Reserved	Reserved
BV7	RUB 200	RUB 200	RUB 200	RUB 200
BV8	Reserved	Reserved	Reserved	Reserved
BV9	RUB 5	RUB 5	RUB 5	RUB 5

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON OFF			
Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
★ ICT104V Interface		OFF	OFF	
Disable Inverse Mode				ON
★ Enable Inverse Mode				OFF

★ Manufacture setting