

# V77E-THB5

## V77E Option Switch Settings: 1(Pulse/ICT104U/MDB/ICT104V)

Supported bill THB 20, 50, 100, 500, 1000 5bills.

V77E dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4	
★	Reject THB 20	ON												
	Accept THB 20	OFF												
	Reject THB 50		ON											
★	Accept THB 50		OFF											
	Reject THB 100			ON										
★	Accept THB 100			OFF										
	Reject THB 500				ON									
★	Accept THB 500				OFF									
	Reject THB 1000					ON								
★	Accept THB 1000					OFF								
	High Acceptance <small>(Note.3)</small>						ON							
★	High Security						OFF							
	<b>Pulse Mode</b>	<b>Other Mode</b>												
	Harness Disable	BA stops working when fishing						ON						
★	Harness Enable	Normal						OFF						
	Inhibit Active High							ON						
★	Inhibit Active Low							OFF						
★	1 pulse / THB 10								OFF	OFF				
	5 pulses / THB 10								ON	OFF				
	10 pulses / THB 10								OFF	ON				
	20 pulses / THB 10								ON	ON				
★	Pulse Speed	50ms LO / 50ms HI								OFF	OFF			
		60ms LO / 300ms HI								ON	OFF			
		30ms LO / 50ms HI								OFF	ON			
		150ms LO / 150ms HI								ON	ON			

★ Manufacture setting

Note : (1) Default setting

(2) Use both 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

**Appendix**

# V77E-THB5(Pulse/ICT104U/MDB/ICT104V)

## DIP SWITCHES SETTING : 3(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
	Credit-Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
	ICT104V Interface		ON	ON	
	MDB Interface		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

## DIP SWITCHES SETTING : 3(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Interface		OFF	ON	
	ICT104V Interface		ON	ON	
	MDB Interface		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

## DIP SWITCHES SETTING : 3(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
	ICT104V Interface		ON	ON	
★	MDB Interface		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

## Currency Assign Data

Interface Bill value	ICT104U	Pulse	MDB	ICT104V
BV1	THB 20	THB 20	THB 20	THB 20
BV2	THB 50	THB 50	THB 50	THB 50
BV3	THB 100	THB 100	THB 100	THB 100
BV4	THB 500	THB 500	THB 500	THB 500
BV5	THB 1000	THB 1000	THB 1000	THB 1000

## DIP SWITCHES SETTING : 3(ICT104V)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Interface		OFF	ON	
★	ICT104V Interface		ON	ON	
	MDB Interface		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting