

V7E/LX7-RUB8

V7E/LX7 Option Switch Settings: 1(Pulse/ICT104V/ICT104U/ MDB)

Supported bill Ruble 10, 50, 100, 200, 500, 1000, 2000, 5000 8bills.

V7E/LX7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject Ruble 10 (Note.4)	ON											
	Accept Ruble 10 (Note.4)	OFF											
	Reject Ruble 50 & 100 & 200		ON										
★	Accept Ruble 50 & 100 & 200		OFF										
	Reject Ruble 500 & 1000			ON									
★	Accept Ruble 500 & 1000			OFF									
	Reject Ruble 2000				ON								
★	Accept Ruble 2000				OFF								
	Reject Ruble 5000					ON							
★	Accept Ruble 5000					OFF							
	Reserved						ON						
★	Reserved						OFF						
	Pulse Mode	Other Mode											
	Harness Disable	BA stops working when fishing								ON			
★	Harness Enable	Normal								OFF			
	Inhibit Active High									ON			
★	Inhibit Active Low									OFF			
★	1 pulse / Ruble 10 & 50									OFF	OFF		
	2 pulses / Ruble 10 & 50									ON	OFF		
	5 pulses / Ruble 10 & 50									OFF	ON		
	20 pulses / Ruble 10 & 50									ON	ON		
★	Pulse Speed	50ms LO / 50ms HI										OFF	OFF
		60ms LO / 300ms HI										ON	OFF
		30ms LO / 50ms HI										OFF	ON
		150ms LO / 150ms HI										ON	ON

★ Manufacture setting

Note : 1.Default setting

- Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.
- Remove the front cover and the dip-switch in on the CPU board.

4. Pulse Mode:

- When Dip 1 is OFF, One Pulse per RUB 10.
- When Dip 1 is ON, One Pulse per RUB 50.

MDB Mode:

- When Dip 1 is OFF, Reject RUB 5000.
- When Dip 1 is ON, Accept RUB 5000.

Appendix

V7E/LX7-RUB8(Pulse/ICT104V/ICT104U/ MDB)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	OFF	
	MDB Interface		ON	ON	
	ICT104V Interface		OFF	ON	
	Reserved				ON
★					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Interface		OFF	OFF	
	MDB Interface		ON	ON	
	ICT104V Interface		OFF	ON	
	Reserved				ON
★					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Interface		OFF	OFF	
	MDB Interface		ON	ON	
	ICT104V Interface		OFF	ON	
	Reserved				ON
★					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	ICT104V	Pulse		MDB	
			When Dip 1 is ON	When Dip 1 is OFF	When Dip 1 is ON	When Dip 1 is OFF
BV1	Ruble 10	Ruble 10			Ruble 50	Ruble 10
BV2	Ruble 50	Ruble 50	Ruble 50	Ruble 50	Ruble 100	Ruble 50
BV3	Ruble 100	Ruble 100	Ruble 100	Ruble 100	Ruble 500	Ruble 100
BV4	Ruble 500	Ruble 500	Ruble 500	Ruble 500	Ruble 1000	Ruble 500
BV5	Ruble 1000	Ruble 1000	Ruble 1000	Ruble 1000	Ruble 5000	Ruble 1000
BV6	Ruble 5000	Ruble 5000	Ruble 5000	Ruble 5000	Ruble 200	
BV7	Ruble 200	Ruble 200	Ruble 200	Ruble 200	Ruble 2000	Ruble 200
BV8	Ruble 2000	Ruble 2000	Ruble 2000	Ruble 2000		Ruble 2000

DIP SWITCHES SETTING : 2(ICT104V)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Interface		OFF	OFF	
	MDB Interface		ON	ON	
★	ICT104V Interface		OFF	ON	
	Reserved				ON
★					OFF

★ Manufacture setting