## V7E Option Switch Settings: 1(Pulse/ICT/M.D.B)

# Supported bill CSD 10, 20, 50, 100, 200, 500, 1000 7 bills.

V7E dip-switch settings and functions:

			_												
	FUNCT	ΓΙΟΝ		SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
	Reject CSD	10 &	20	ON											
*	Accept CSD	10 &	20	OFF											
	Reject CSD	50 &	100		ON										
*	Accept CSD	50 &	100		OFF										
	Reject CSD	200				ON									
*	Accept CSD	200				OFF									
	Reject CSD	500					ON								
*	Accept CSD	500					OFF								
	Reject CSD	1000						ON							
*	Accept CSD	1000						OFF							
	Reser	ved							ON						
*	Reser	ved							OFF						
	Harness [	Disable		ON											
*	Harness Enable			OFF			OFF								
	Inhibit Active High								ON						
*	Inhibit Active Low			C					OFF						
*	1 pulse / CSD 10									OFF	OFF				
	5 pulse / CSD 10					ON	OFF								
	10 pulse /	CSD 10								OFF	ON				
	25 pulse /	CSD 10							ON	ON					
*				50n	ns on	/ 50	ms of	ff						OFF	OFF
	Pulse Speed			60ms on / 300ms off			ff						ON	OFF	
	i disc opeca			30ms on / 50ms off									OFF	ON	
				150n	ns on	/ 150	ms of	ff						ON	ON

- ★ Manufacture setting
- Note: (1) Reset the bill acceptor after setting the dip switch.
  - (2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

#### **DIP SWITCHES SETTING: 2(Pulse)**

*	FUNCTION	SW1	SW2	SW3	SW4
	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
*	ICT Interface		OFF	ON	
	Pulse Mode		ON	OFF	
	M.D.B Interface		ON	ON	
*	Reserved				ON
	Reserved		OFF		

#### **DIP SWITCHES SETTING: 3(ICT)**

	FUNCTION	SW1	SW2	SW3	SW4
*	Reserved -				
	ICT Interface		OFF	ON	
	Pulse Mode		ON	OFF	
	M.D.B Interface		ON	ON	
*	Reserved		ON		
	Reserved				

### **DIP SWITCHES SETTING: 4(M.D.B)**

	FUNCTION	SW1	SW2	SW3	SW4
*	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	ICT Interface		OFF	ON	
	Pulse Mode		ON	OFF	
*	M.D.B Interface		ON	ON	
	Reserved				ON
*	i vesei veu		OFF		

<sup>★</sup> Manufacture setting

<sup>•</sup> Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.