

BS7-RUR5

BS7 Option Switch Settings: 1 (Special Pulse/ICT004/MDB)

Supported bill Ruble 10, 50, 100, 200, 500 5bills.

BS7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8
★	Reject Ruble 10 (Note 1.)	ON							
★	Accept Ruble 10 (Note 1.)	OFF							
★	Reject Ruble 50		ON						
★	Accept Ruble 50		OFF						
★	Reject Ruble 100			ON					
★	Accept Ruble 100			OFF					
★	Reject Ruble 200				ON				
★	Accept Ruble 200				OFF				
★	Reject Ruble 500					ON			
★	Accept Ruble 500					OFF			
★	Reserved						ON		
★	Reserved						OFF		
★	Harness Disable							ON	
★	Harness Enable							OFF	
★	Inhibit Active High								ON
★	Inhibit Active Low								OFF

◆ Factory configuration has all switches in the OFF position.

Note :

(1) Dip Switch 1 is for Pulse

When SW1 Dip1 is OFF(Accept 10 Rubles),
Pulse==>10 Rubles=1 Pulse, 50 Rubles=5 Pulse,100 Rubles=10 Pulse,
200 Rubles=20 Pulse, 500 Rubles=50 Pulse....

When SW1 Dip1 is ON (Reject 10 Rubles),
Pulse==>50 Rubles=1 Pulse, 100 Rubles=2 Pulse,200 Rubles=4 Pulse,
500 Rubles=10 Pulse....

BS7-RUR5(Special Pulse/ICT004/MDB)

BS7 Interface Settings: 2 (Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	1 pulse / Ruble 10	OFF	OFF		
	2 pulse / Ruble 10	ON	OFF		
	5 pulse / Ruble 10	OFF	ON		
★	10 pulse / Ruble 10	ON	ON		
	50ms LO / 50ms HI			OFF	OFF
	60ms LO / 300ms HI			ON	OFF
	30ms LO / 50ms HI			OFF	ON
	150ms LO / 150ms HI			ON	ON

★ Manufacture setting

BS7 Interface Settings: 2 (Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	1 pulse / Ruble 50	OFF	OFF		
	2 pulse / Ruble 50	ON	OFF		
	5 pulse / Ruble 50	OFF	ON		
	10 pulse / Ruble 50	ON	ON		
★	50ms LO / 50ms HI			OFF	OFF
	60ms LO / 300ms HI			ON	OFF
	30ms LO / 50ms HI			OFF	ON
	150ms LO / 150ms HI			ON	ON

★ Manufacture setting

BS7 Interface Settings: 3 (ICT004)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	Pulse Mode		ON	OFF	
	MDB Interface		OFF	OFF	
★	ICT004 Interface		OFF	ON	
★	Reserved				ON
					OFF

BS7 Interface Settings: 3 (Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
	Credit-Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	MDB Interface		OFF	OFF	
	ICT004 Interface		OFF	ON	
★	Reserved				ON
					OFF

BS7 Interface Settings: 3 (MDB)

	INTERFACE	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
★	MDB Interface		OFF	OFF	
	ICT004 Interface		OFF	ON	
★	Reserved				ON
					OFF

Currency Assign Data

Interface Bill value	ICT004	Pulse	MDB
BV1	Ruble 10	Ruble 10	Ruble 10
BV2	Ruble 50	Ruble 50	Ruble 50
BV3	Ruble 100	Ruble 100	Ruble 100
BV4	Ruble 200	Ruble 200	Ruble 200
BV5	Ruble 500	Ruble 500	Ruble 500