

BS7-RUR7

BS7 Option Switch Settings: 1 (Pulse/ICT004/MDB)

Supported bill Ruble 50, 100, 200, 500, 1000, 2000, 5000 7bills.

BS7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject Ruble 50 & 100	ON											
★	Accept Ruble 50 & 100	OFF											
★	Reject Ruble 200		ON										
★	Accept Ruble 200		OFF										
★	Reject Ruble 500 & 1000			ON									
★	Accept Ruble 500 & 1000			OFF									
★	Reject Ruble 2000				ON								
★	Accept Ruble 2000				OFF								
★	Reject Ruble 5000					ON							
★	Accept Ruble 5000					OFF							
★	Reserved					ON							
★	Reserved					OFF							
★	Harness Disable						ON						
★	Harness Enable						OFF						
★	Inhibit Active High							ON					
★	Inhibit Active Low							OFF					
★	1 pulse / Ruble 50								OFF	OFF			
★	5 pulses / Ruble 50								ON	OFF			
★	10 pulses / Ruble 50								OFF	ON			
★	50 pulses / Ruble 50								ON	ON			
★	Pulse Speed		50ms LO / 50ms HI								OFF	OFF	
			60ms LO / 300ms HI								ON	OFF	
			30ms LO / 50ms HI								OFF	ON	
			150ms LO / 150ms HI								ON	ON	

◆ Factory configuration has all switches in the OFF position.

Note : (1) Please reset the bill acceptor after any changes on Dip switch.

(2) SW6 . SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

BS7-RUR7(Pulse/ICT004/MDB)

BS7 Interface Settings: 3 (ICT004)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	Pulse Mode		ON	OFF	
★	MDB Interface		OFF	OFF	
★	ICT004 Interface		OFF	ON	
★	Reserved				ON
					OFF

BS7 Interface Settings: 3 (Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
	Credit-Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	MDB Interface		OFF	OFF	
	ICT004 Interface		OFF	ON	
★	Reserved				ON
					OFF

BS7 Interface Settings: 3 (MDB)

	INTERFACE	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
★	Pulse Mode		ON	OFF	
★	MDB Interface		OFF	OFF	
	ICT004 Interface		OFF	ON	
★	Reserved				ON
					OFF

Currency Assign Data

Interface Bill value	ICT004	Pulse	MDB
BV1			
BV2	Ruble 50	Ruble 50	Ruble 50
BV3	Ruble 100	Ruble 100	Ruble 100
BV4	Ruble 500	Ruble 500	Ruble 500
BV5	Ruble 1000	Ruble 1000	Ruble 1000
BV6	Ruble 5000	Ruble 5000	Ruble 5000
BV7	Ruble 200	Ruble 200	Ruble 200
BV8	Ruble 2000	Ruble 2000	Ruble 2000