

L77F&PL77-PLN5

L77F&PL77-P3/P6 DIP SWITCHES SETTING : 1(Pulse/ICT)

Supported bill zloty 10, 20, 50, 100, 200 5bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / zloty 10	OFF	OFF	OFF							
2 Pulse / zloty 10	OFF	OFF	ON							
3 Pulse / zloty 10	OFF	ON	OFF							
4 Pulse / zloty 10	OFF	ON	ON							
5 Pulse / zloty 10	ON	OFF	OFF							
10 Pulse / zloty 10	ON	OFF	ON							
20 Pulse / zloty 10	ON	ON	OFF							
100 Pulse / zloty 10	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low				ON						
Inhibit level Active High				OFF						
★ Accept zloty 10						ON				
Reject zloty 10						OFF				
★ Accept zloty 20							ON			
Reject zloty 20							OFF			
★ Accept zloty 50								ON		
Reject zloty 50								OFF		
★ Accept zloty 100									ON	
Reject zloty 100									OFF	
★ Accept zloty 200										ON
Reject zloty 200										OFF

DIP SWITCHES SETTING : 2

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON		
ICT104U Protocol Mode		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

Currency Assign Data

Interface Bill value	Pulse	ICT104U
BV1	zloty 10	zloty 10
BV2	zloty 20	zloty 20
BV3	zloty 50	zloty 50
BV4	zloty 100	zloty 100
BV5	zloty 200	zloty 200

★ Manufacture setting

Note:(1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.