

L77F/PL77-EUR4

L77F/PL77-P3/P6 DIP SWITCHES SETTING : 1(Pulse/ccTalk/Smiley Parallel)

Supported bill € 5, 10, 20, 50 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / € 5	OFF	OFF	OFF							
	2 Pulse / € 5	OFF	OFF	ON							
	3 Pulse / € 5	OFF	ON	OFF							
	4 Pulse / € 5	OFF	ON	ON							
	5 Pulse / € 5	ON	OFF	OFF							
	10 Pulse / € 5	ON	OFF	ON							
	20 Pulse / € 5	ON	ON	OFF							
	100 Pulse / € 5	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept € 5				ON						
★	Reject € 5				OFF						
★	Accept € 10				ON						
	Reject € 10				OFF						
★	Accept € 20				ON						
	Reject € 20				OFF						
★	Accept € 50				ON						
	Reject € 50				OFF						
★	Accept Normal				ON						
	Reject € 5(2002) & 10(2002)				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

L77F/PL77-EUR4(Pulse/ccTalk/Smiley Parallel)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
	Smiley Mode		ON	ON	
	ccTalk Interface		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ccTalk)

	FUNCTION	SW1	SW2	SW3	SW4
★	16 Bit	ON			
	8 Bit	OFF			
	Pulse Mode		ON	OFF	
	ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
	Smiley Mode		ON	ON	
★	ccTalk Interface		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(Smiley Parallel)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
	ccTalk Parameters Restore Switch (Please see Note.3 for Detail)		OFF	ON	
★	Smiley Mode		ON	ON	
	ccTalk Interface		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ccTalk	Smiley Parallel
BV1	€ 5	€ 5	€ 5
BV2	€ 10	€ 10	€ 10
BV3	€ 20	€ 20	€ 20
BV4	€ 50	€ 50	€ 50