

L77F/PL77-SEK4

L77F/PL77 DIP SWITCHES SETTING : 1(Pulse/Out of service/ICT104U)

Supported bill SEK 20, 50, 100, 200 4bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / SEK 10	OFF	OFF	OFF							
2 Pulses / SEK 10	OFF	OFF	ON							
3 Pulses / SEK 10	OFF	ON	OFF							
4 Pulses / SEK 10	OFF	ON	ON							
5 Pulses / SEK 10	ON	OFF	OFF							
10 Pulses / SEK 10	ON	OFF	ON							
20 Pulses / SEK 10	ON	ON	OFF							
100 Pulses / SEK 10	ON	ON	ON							
★ Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
★ Inhibit level Active Low				ON						
★ Inhibit level Active High				OFF						
★ Accept SEK 20					ON					
★ Reject SEK 20					OFF					
★ Accept SEK 50						ON				
★ Reject SEK 50						OFF				
★ Accept SEK 100							ON			
★ Reject SEK 100							OFF			
★ Accept SEK 200								ON		
★ Reject SEK 200								OFF		
★ Reserve										ON
★ Reserve										OFF

DIP SWITCHES SETTING : 2 Currency Assign Data

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal High	ON			
Credit-Pulse Normal Low	OFF			
★ Pulse Mode		ON		
★ ICT104U Protocol Mode		OFF		
★ Reserved			ON	
★ Reserved			OFF	
★ Reserved				ON
★ Reserved				OFF

Interface	Pulse	ICT104U
BV1	SEK 20	SEK 20
BV2	SEK 50	SEK 50
BV3	SEK 100	SEK 100
BV4	SEK 200	SEK 200

★ Manufacture setting

Note:(1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

(3)Out of service:Normal Low,Error High.