

L77F/PL77-UYU7

L77F&PL77-P3/P6 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill UYU 20, 50, 100, 200, 500, 1000, 2000 7bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / UYU 10	OFF	OFF	OFF							
	2 Pulse / UYU 10	OFF	OFF	ON							
	3 Pulse / UYU 10	OFF	ON	OFF							
	4 Pulse / UYU 10	OFF	ON	ON							
	5 Pulse / UYU 10	ON	OFF	OFF							
	10 Pulse / UYU 10	ON	OFF	ON							
	20 Pulse / UYU 10	ON	ON	OFF							
	100 Pulse / UYU 10	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept UYU 20					ON					
	Reject UYU 20					OFF					
★	Accept UYU 50						ON				
	Reject UYU 50						OFF				
★	Accept UYU 100							ON			
	Reject UYU 100							OFF			
★	Accept UYU 200 & 500								ON		
	Reject UYU 200 & 500								OFF		
★	Accept UYU 1000 & 2000									ON	
	Reject UYU 1000 & 2000									OFF	

★ Manufacture setting

Note:(1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
	★ Pulse Mode		ON		
	ICT104U Interface Mode		OFF		
	Reserved			ON	
★	Reserved			OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	Pulse
BV1	\$ 20	\$ 20
BV2	\$ 50	\$ 50
BV3	\$ 100	\$ 100
BV4	\$ 200	\$ 200
BV5	\$ 500	\$ 500
BV6	\$ 1000	\$ 1000
BV7	\$ 2000	\$ 2000