



BGL5

L83 DIP SWITCHES SETTING : 1(Pulse/ICT)

Supported bill BGL 5(99), 10(99), 20(99), 50(99, 06),
100(03) 5 bills.

FUNCTION		SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / BGL 5	OFF	OFF	OFF							
	2 Pulse / BGL 5	OFF	OFF	ON							
	3 Pulse / BGL 5	OFF	ON	OFF							
	4 Pulse / BGL 5	OFF	ON	ON							
	5 Pulse / BGL 5	ON	OFF	OFF							
	10 Pulse / BGL 5	ON	OFF	ON							
	20 Pulse / BGL 5	ON	ON	OFF							
	100 Pulse / BGL 5	ON	ON	ON							
	Fast output Pulse	Lo= 50ms Hi=100ms			ON						
★	Slow output Pulse	Lo= 50ms Hi=300ms			OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept BGL 5						ON				
	Reject BGL 5						OFF				
★	Accept BGL 10							ON			
	Reject BGL 10							OFF			
★	Accept BGL 20								ON		
	Reject BGL 20								OFF		
★	Accept BGL 50									ON	
	Reject BGL 50									OFF	
★	Accept BGL 100										ON
	Reject BGL 100										OFF

DIP SWITCHES SETTING : 2

FUNCTION		SW1	SW2	SW3	SW4	
★	Pulse Normal High	ON				
	Pulse Normal Low	OFF				
	Pulse Mode					ON
	ICT Protocol Mode					OFF
Reserved				ON		
				OFF		
				ON		
				OFF		

★ Manufacture setting

Note:(1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

