



CZK6

L83 DIP SWITCHES SETTING : 1(RS232 A1/Pulse)

Supported bill CZK 100, 200, 500, 1000, 2000, 5000

6bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / CZK 100	OFF	OFF	OFF							
2 Pulses / CZK 100	OFF	OFF	ON							
3 Pulses / CZK 100	OFF	ON	OFF							
4 Pulses / CZK 100	OFF	ON	ON							
5 Pulses / CZK 100	ON	OFF	OFF							
10 Pulses / CZK 100	ON	OFF	ON							
20 Pulses / CZK 100	ON	ON	OFF							
100 Pulses / CZK 100	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
Inhibit level Active High					OFF					
★ Accept CZK 100						ON				
★ Reject CZK 100						OFF				
★ Accept CZK 200 & 500							ON			
★ Reject CZK 200 & 500							OFF			
★ Accept CZK 1000								ON		
★ Reject CZK 1000								OFF		
★ Accept CZK 2000									ON	
★ Reject CZK 2000									OFF	
★ Accept CZK 5000										ON
★ Reject CZK 5000										OFF

★ Manufacture setting

Note:(1)Please reset the bill acceptor after any changes on Dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

L83-CZK6(RS232 A1/Pulse)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
RS232 A1 Mode		OFF		
★ Reserved			ON	
			OFF	
				ON
★				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(RS232 A1)

FUNCTION	SW1	SW2	SW3	SW4
Reserve	ON			
Reserve	OFF			
Pulse Mode		ON		
★ RS232 A1 Mode		OFF		
★ Reserved			ON	
			OFF	
				ON
★				OFF

★ Manufacture setting