

## L83-EUR6

### L83 Option Switch Settings : 1(Pulse/ICT104U/MDB/ccNet)

Supported bill € 5, 10, 20, 50, 100, 200 6bills.

L83 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / € 5	OFF	OFF	OFF							
2 Pulse / € 5	OFF	OFF	ON							
3 Pulse / € 5	OFF	ON	OFF							
4 Pulse / € 5	OFF	ON	ON							
5 Pulse / € 5	ON	OFF	OFF							
10 Pulse / € 5	ON	OFF	ON							
20 Pulse / € 5	ON	ON	OFF							
100 Pulse / € 5	ON	ON	ON							
Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept € 5 & 10						ON				
Reject € 5 & 10						OFF				
★ Accept € 20 & 50							ON			
Reject € 20 & 50							OFF			
★ Accept € 100								ON		
Reject € 100								OFF		
★ Accept € 200									ON	
Reject € 200									OFF	
★ Accept Normal										ON
Reject € 5(2002) & 10(2002)										OFF

◆ Manufacture Default setting.

Note : (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip Switch 1 to 5 are only for Pulse mode.

## L83-EUR6(Pulse/ICT104U/MDB/ccNet)

### Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Interface		ON	OFF	
MDB Interface		ON	ON	
ccNet Interface		OFF	OFF	
ICT104U Interface		OFF	ON	
Reserved				ON
★				OFF

★ Manufacture setting

### Interface Settings: 2(ICT104U)

INTERFACE	SW1	SW2	SW3	SW4
Reserved	ON			
★	OFF			
Pulse Interface		ON	OFF	
MDB Interface		ON	ON	
ccNet Interface		OFF	OFF	
★ ICT104U Interface		OFF	ON	
Reserved				ON
★				OFF

★ Manufacture setting

### Interface Settings: 2(ccNet)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Interface		ON	OFF	
MDB Interface		ON	ON	
★ ccNet Interface		OFF	OFF	
ICT104U Interface		OFF	ON	
Reserved				ON
★				OFF

★ Manufacture setting

### Currency Assign Data

Interface Bill value	MDB	Pulse	ccNet	ICT104U
BV1	€ 5	€ 5	€ 5	€ 5
BV2	€ 10	€ 10	€ 10	€ 10
BV3	€ 20	€ 20	€ 20	€ 20
BV4	€ 50	€ 50	€ 50	€ 50
BV5	€ 100	€ 100	€ 100	€ 100
BV6	€ 200	€ 200	€ 200	€ 200

### Interface Settings: 2(MDB)

INTERFACE	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Interface		ON	OFF	
★ MDB Interface		ON	ON	
ccNet Interface		OFF	OFF	
ICT104U Interface		OFF	ON	
Reserved				ON
★				OFF

★ Manufacture setting