

PLN5

L83 DIP SWITCHES SETTING : 1(Pulse/ICT)

Supported bill zloty 10, 20, 50, 100, 200 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / zloty 10	OFF	OFF	OFF							
	2 Pulse / zloty 10	OFF	OFF	ON							
	3 Pulse / zloty 10	OFF	ON	OFF							
	4 Pulse / zloty 10	OFF	ON	ON							
	5 Pulse / zloty 10	ON	OFF	OFF							
	10 Pulse / zloty 10	ON	OFF	ON							
	20 Pulse / zloty 10	ON	ON	OFF							
	100 Pulse / zloty 10	ON	ON	ON							
	Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★	Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept zloty 10						ON				
	Reject zloty 10						OFF				
★	Accept zloty 20							ON			
	Reject zloty 20							OFF			
★	Accept zloty 50								ON		
	Reject zloty 50								OFF		
★	Accept zloty 100									ON	
	Reject zloty 100									OFF	
★	Accept zloty 200										ON
	Reject zloty 200										OFF

★ Manufacture setting

Note:(1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4	
★	Pulse Normal High	ON				
	Pulse Normal Low	OFF				
★	Pulse Mode					ON
	ICT Protocol Mode					OFF
	Reserved			ON		
★				OFF		
	Reserved				ON	
★					OFF	

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT
BV1	Zloty 10	Zloty 10
BV2	Zloty 20	Zloty 20
BV3	Zloty 50	Zloty 50
BV4	Zloty 100	Zloty 100
BV5	Zloty 200	Zloty 200